

Introduction:

Super power, compact size and comfortable to hold, you want it all? People always thought that strong power should match with large size, SMOK will say NO to that. The 350W output is the maximum output power in the global with a so much compact size. It is just the GX350 kit. And GX350 mod max output power can up to 350W when powered by 4 x 18650 batteries. And the Micro-USB port supports firmware upgrading. When matching with the cloud beast TFBV8, you will enjoy fantastic clouds.

Specifications

GX 350 Mod

Size: 59.3x40.4x84.5mm
Standby Current: <500uA
Output Power: 6W-350W (Max)
Temperature Range: 200°F-600°F / 100°C-315°C
Resistance Range: 0.10Ω-3.00Ω (VW Mode) / 0.06Ω-3.00Ω (TC Mode)

TFV8 Tank

Size: 24.5x69mm
Weight: 74g
Material: Stainless Steel
Thread: 510
Capacity: 5.5ml (with V8-T8) / 6.0ml (with V8-Q4)

1

Verification

- Using your Smartphone or PC to visit SMOK official website: <http://www.smoktech.com/support/>
- Scratch off the coating of the security label on packing box to get the 16 anti-fake codes. Fill them into the input box on the webpage to verify. The result will come out after a few seconds.
- If you have any question, please contact SMOK consultant via e-mail, phone or our website to get more help.

Welcome to download our APP: Vaping Tour, share your vaping experience and communicate with global vapor fans.



3

User Guide

Preparation before use:

- Please make sure the battery you used is according with the BATTERY WARNING CARD.
- Before enjoy vaping, please make sure the tank is filled with enough e-juice.

Install Battery

- Slide and open the battery cover as the picture shows;
- Place the batteries into the device according to the correct directions;
- Close the battery cover.



5

Attach Atomize

GX350 atomizer head is using a new generation of elastic-touch design perfectly fit 510 connector atomizers. Please confirm that the atomizer head should not be blocked by any stems before attachment:
1) Connect the atomizer to the device and tighten it clockwise.
2) After the device is powered on, please press the Power Button to vape.

Mod Operations

1. Power On:

While the device is off power, fast click Power Button 5 times in 2s to start up. The screen successively shows "SMOK";

2. Vaping:

While the device is power on, hold Power Button to vape (it will be forced to stop working when one vaping is longer than 12s, release once to vape again);

Fast press the Power Button 5 times to lock or unlock

3. Screen Unlocked Status:

7

Icon	Name	Brief introduction
	MODE Switch	TEMP MODE/WATT MODE
	TEMP MODE	1.Choose different effect by pressing Power Button:15-350W 2.COIL TYPE: T-NI, T-TI, T-SS 3.Adjust Temperature coefficient of resistance
	WATT MODE	Choose different effect by pressing Power Button: STRENGTH MAX/HARD/NORM/SOFT/MIN
	PUFFS	ALERADY: Puff numbers you have taken; MAX PUFFS: Set limited puff numbers; NEVER: Represents unlimited puffs; PUFFS RESET: puff counter clearing function
	Setting	Press Power Button to enter sub-menu
	SCR TIME	STEALTH ON: in this mode the display is off. Choose STEALTH OFF, and then set screen saver time (15 seconds to 240 seconds).
	SCR LOCK	AUTO LOCKED ON; AUTO LOCKED OFF

9

TC Mode

TC Mode is available when GX350 works with a TC type atomizer.

- Enter TC Mode: switch between TC Mode and VW Mode by pressing Power Button + DOWN Button simultaneously while screen is unlocked. Use POWER+ UP Button simultaneously to switch from 15W to 350W.
- In the TC Mode, please use the UP / DOWN Button to adjust the temperature settings with an increment/decrement of 10 Fahrenheit degrees (about 5 Celsius degrees) to get the best preferred settings.
- Enter into Coil Material Selection menu. There are three options of Temperature Sensing Coil Material for you to choose: T-NI, T-TI, T-SS.
- Enter into Adjustable Initial Resistance. You can adjust the initial resistance of your atomizer by pressing the Up/Down button.

Tank Operations

How to fill with e-liquid:

- Hold the tank with one of your hands, and use another one to press top cap and move it counterclockwise.



- Add e-liquid through the slot, and pay attention not to drip it into the central airflow tube.



13

Control air input:

Rotate the adjustable airflow ring to control air input.



Adjustable Airflow Ring

If you need any additional information or have any questions about the products or its use, please contact your local SMOK agent or to visit our website www.smoktech.com

15

LEGAL DISCLAIMER

Underage sale is prohibited. Depending on your country/region legal smoking age. 18+ and over 21+ in other countries/regions.

WARNING

This product is not intended for use by persons under legal smoking age, nonsmokers, women who are pregnant or breastfeeding, or persons with or at risk of heart disease, high blood pressure, diabetes, or taking medicine for depression or asthma.

Appendix 2 Screen Prompts Table

Prompts	Details
"SMOK"	Power on success
"SMOK", "GOODBYE"	Power off success
BATTERY LOW	Battery power isn't enough, change a battery
HIGH INPUT	Battery voltage is higher than need, change a battery
NO COIL	Atomizer hasn't been detected, attach an atomizer
NEW COIL?	Atomizer has been detected under TC Mode
OHMS TOO LOW	Low resistance value has been detected, replace atomizer

17

The Kit Includes

- | | |
|---|----------------|
| 1 x GX 350 Mod | 1 x TFBV8 Tank |
| 1 x V8-T8 Octuple Coil Head (0.15Ω) (Pre-installed) | |
| 1 x V8-Q4 Quadruple Coil Head (0.15Ω) | 1 x USB Cable |
| 1 x User Manual | Spare Parts |

Warranty


GX350 Kit Warranty Period: 6 Months from the Purchase Date. Within the 6 Months, some items may not be eligible for service due to misuse, damage, or other failures caused other than by manufacturer defects or premature failure. Please contact SMOK Authorized Vendor for more information and terms of service. The "GX350 Kit Customer Card" is an important proof for customers to get warranty service, please keep it. And read the card carefully and fill it out correctly. Warranty requests must be accompanied by this card. For more warranty policy and process, please visit our official website: <http://www.smoktech.com/support/>

2

Components



4



6

- Press Power + DOWN Button simultaneously to choose working mode between TC Mode and VW Mode;
- Press Power + UP Button simultaneously to choose different effect from Min/Norm/Soft/Hard/Max in WATT MODE or 15-350W in TEMP MODE.
- Press UP / DOWN Button to adjust the temperature or wattage settings;

4. Screen Locked Status:

Hold the Power Button for 5s and choose POWER OFF to power off.

- Power Off:** While the device is locked, hold Power Button for 5s, choose POWER OFF, and the screen turns off, which means the device is power off.

- Saving:** All the settings will be automatically saved while settings done. No need to reset after power on.

- Menus & Prompts:** After startup, fast press the POWER Button 3 times in 2s, then you will go to the operation menu. At the same time, long-press on the POWER Button has confirmed function; UP/DOWN Button could do menu moves.

8

	CONTRAST	Contrast range is 10-100, you can increase/decrease by UP/DOWN Button
	SCR DIR	Screen can rotate in 180 degree
	ADJ OHM	Can be adjusted by UP/DOWN Button
	DOWNLOAD	Upgrade the firmware by switch EXIT or ENTER
	Power ON/OFF	POWER ON: POWER OFF with "SMOK", "GOODBYE"
	Unlock/Lock	Screen locked status, fast press Power Button 5 times to unlock; Screen unlocked status, fast press Power Button to lock
	Over temperature	Stop vaping, you can vape again after 30s

10

- When the screen shows "TEMPERATURE PROTECTED", the heating coil reached the maximum allowed temperature during the Vaping. If it happens, the GX350 will continue to fire, but will not be able to provide the desired wattage.

VW Mode

GX350 VW Mode is available for all types of atomizers.

- Enter VW Mode: switch between TC Mode and VW Mode by pressing Power Button + DOWN Button simultaneously while screen is unlocked.
- Use POWER+ UP Button simultaneously to switch among STRENGTH MAX/HARD/ NORM/SOFT/MIN.
- In the WATT Mode, use the UP / DOWN Button to adjust the wattage settings with an increment/decrement of 0.1W to get the best preferred wattage.

12

- Close the cap carefully and firmly. Then let it stand for several minutes to get the organic cotton completely saturated.



Replace atomizer core:

Firstly, screw the base part off the tank; then screw the atomizer core off the base part, and replace with a new one.



14

Attentions

- Before use please read the manual carefully.
- Connect the atomizer to a power source that is suitable for its intended use.
- Please avoid making the e-liquid into your mouth directly.
- Please do not keep the liquid inside the atomizer if the device is not going to be used for a long period.
- Please refill the tank when the e-liquid is nearly used out to avoid dry-burning of the atomizer.
- Please do not drop, throw or mishandle this product as the outer shell or inner components may become damaged.
- In order to prolong the operation of your product, please keep it away from excessive temperature and humid environment.
- Please keep this product away from children and pregnant women.



16

Appendix 1 Key Function Table

Key	Function(Screen Unlock Status)	Function(Screen Locked Status)
Power	Fast click 5 times in 2s - Power On Fast click 3 times in 2s - Screen Locked Hold on - Vape Release - Standby	Long press 5s - choose Power Off to turn off Fast click 5 times - Unlock Screen
UP	Click Down - Increase the temperature (TC Mode) Click Down - Increase the wattage (VW Mode)	
DOWN	Click Down - reduce the temperature (TC Mode) Click Down - reduce the wattage (VW Mode)	
Power + UP	Click Down - Change TC Effect (15-350W) or VW Effect (MAX/HARD/NORM/SOFT/MIN)	
Power + DOWN	Click Down - Change Working Mode (TC / VW)	

OHMS TOO HIGH	High resistance value has been detected, replace atomizer
COIL SHORT	Short circuit has been detected, replace atomizer
TEMPERATURE PROTECTION	Temperature protection under TC Mode
DRY COIL NO LIQUIDRY COIL NO LIQUID	Atomizer coil is heating without liquid under TC Mode, fill juice

18