

Target Pro

Thank you for choosing Vaporesso Products!

Target Pro is the most innovative vaping product, featured in its unique shape for a great fit in the hand, and a trigger-style vape button that is easy to use for both left-handed and right-handed users. It also brings a revolutionary atomizing technology: CCELL coils, which are made out of a porous material that ensure not only better flavor but also no splashing, no dry hits and guarantee a longer life cycle. This device has a superb design, comes with temperature control and variable wattage functions, and can power up to 75w using a single 18650 battery. It's magnetic battery cover is very user-friendly. This fine kit will bring you a sensational vaping experience.

Please read this manual carefully to ensure proper use. For additional information or questions regarding this product or its use, please visit www.vaporesso.com

Characteristic:

- Target Pro Box Mod Output 75W supports VT: 0.05Ω-1.0Ω VW:0.15Ω-3Ω
- 4 Adjusting modes: Variable Temperature: Ni/SS/Ti/TCR Variable Wattage, Stainless Steel, Titanium
- TCR Mode Available at Firmware Update
- Automatic Atomizer Recognition
- Aqueous Ceramic Coated Surface


Package include

- 1 Complete Target Pro Tank (CCELL SS 0.5Ω pre-installed)
- 1 Target Pro Box
- 1 Extra CCELL SS 0.6Ω
- 1 USB cable
- 1 User Manual

Specification

Target Pro Tank

Diameter: 22mm
Length: 53.5mm
Weight: 60g
Capacity: 2.5ml



Target Pro Box

Dimension: 92x48x27 mm
Weight: 180g
Temperature Range: 100°C-315°C/200F-600F
Output Wattage: 5w to 75w
Suitable atomizer: VT: 0.05Ω-1.0Ω VW: 0.15Ω-3Ω
Output Modes: VT/Ni/SS/Ti/TCR
Standby Current: < 50uA
Voltage range: 0-9V
Battery Cell: Lithium 18650
Casting: Zinc Alloy and stainless steel
Thread: 510 thread
Display: OLED
USB Updatable and customizable firmware



Filling E-juice

1. To refill the E-juice from the top, simply twist open the lid.
2. Once filled, twist back shut and resume use.

Changing the atomizer

1. Remove the tank from the battery and turn the tank upside down;
2. Unscrew the air flow base and carefully set your tank aside;
3. Unscrew the atomizer unit counterclockwise;
4. Once removed, discard the used one. Screw the new atomizer unit clockwise into the air flow base;
5. Screw the air flow base back to the tank body.

Warning:

- When using a new atomizer, after filling E-juice, let the tank stand for 2 minutes, so the ceramic can be saturated with juice before firing;
- Refill the tank before the tank become completely empty in order to avoid dry burning or damage to the atomizer.

Target Pro Box Operation Guide

1. **Switch on/off:** after a battery is installed, press the power button 5 speedy times to switch on the mod, "Vaporesso" will appear on the screen.
2. **Screen Display:** after switch on, OLED displays voltage, resistance value, battery level, temperature, output wattage; the display will shut off if unused for 15s, the screen will be relit by pressing the fire button.
3. **Automatic atomizer recognition:** the mod will read the coil's resistance as soon as the connection is detected. It will also recognize coil type, when a kanthal coil is used, the mod will shift from TC to wattage mode automatically.
4. **To vape:** Long pressing the power button to vape, it will initiate 10s' counting down to limit maximum time for one puff; pressing longer than 10s will shut it down, "over 10s" will be shown on the screen.
5. **Adjust wattage:** Press the " + " - " to adjust the wattage at 0.1 increment, long-press will adjust at an accelerated rate.
6. **To rotate the screen display:** fast click fire button 3 times.
7. **To lock the diameters:** Press the " + " steadily

while press the power button simultaneously, " SYSTEM LOCKED" appears on the screen. Repeat the motion to unlock.

8. **Charging:** Plug in the Micro USB cable to charge the battery. OLED display current battery level (0%, 20%, 50%, 80%, and 100%). The display will remain lit while charging.

Temperature Control

1. **Switch 4 modes:** Press " + " - " together to switch between wattage mode and different temperature control modes.
2. **Adjust temperature:** At temperature control mode, press the " + " - " to adjust the temperature at 10°F or 5°C, long-press will adjust at an accelerated rate.
3. **Lock/Unlock resistance:** At temperature control, press the " - " and power button simultaneously for 2s will lock/unlock the resistance level, " 🔒 " will appear on the display. Attach a new atomizer will not change the locked resistance.
4. **Automatic atomizer recognition:** To achieve better temperature control effect, the mod will ask the user if the new atomizer is attached. " OLD LOAD-, NEW

LOAD + " will appear on the display. If a new atomizer is attached, press " + ", the mod will read new resistance; if not, press " - ", the mod will read locked resistance.

5. **Firmware update and customizing:** The firmware can be updated and customized through a simple software that can be downloaded directly from our website. The software will be made to run on Windows systems and will be available in Chinese or English. It will also include a "help" sections for urgent questions. The directions on how to use our software will be found on our website and Facebook page.

Target Pro Box Protection functions

- Over - temperature protection (PCBA temperature less than 65°C)
- Low battery protection
- Short-circuit protection
- Low resistance protection (Resistance \geq 0.13Ω)
- Reverse connection of the battery power terminal
- Over-charge protection and over discharge protection (2.9v-4.3v)
- No atomizer detection protection
- Over current protection

Caution

1. The Target Pro is intended for usage by people over 18, NOT by non-smokers, children, pregnant or breastfeeding women, people with or at risk of heart disease, or people taking medication for depression or asthma. The electronic cigarette is not a smoking cessation device.
2. Please keep this unit out of reach of children or pets.
3. Please don't drop, throw or abuse your Target Pro, it may cause damage.
4. Please keep the battery dry.
5. Do not place it in extremely temperatures.
6. Do not try to disassemble the battery.
7. This device does not mean to be used as a nicotine replacement therapy for smoking cessation.