



Powerpod Air 5 User Manual

Features and Specifications


- Product Name: Powerpod Air 5
- Capacity: 5000mAh
- Product Dimensions: 121*41*14mm
- Net Weight: 138g
- Battery Type: Lithium Polymer
- Output Power: 5w (max)
- Rated Input: 5V/1A
- Rated Output: 5V/1A
- Working Temperature: 0°C~45°C
- Storage Temperature: -10°C~45°C
- Working Humidity: ≤90%
- Storage Humidity: 20%~65%
- Indicators: 4 power level LED indicators
- Protection Functions: Built-in protection for short circuit, over charge/discharge
- Device Supported: mobile phones, tablets, portable media players, handheld game consoles, Bluetooth devices and more

Accessory list




Micro USB Charging Cable

Interfaces and Buttons



- ① USB1 5V/1A
- ② DC IN Micro-USB (5 PIN)
- ③ Power Level Indicators
LED1-LED4(From left to right)
- ④ ON/OFF Power Button
- ⑤ LED Torch Light


How to Use




Use to charge smart phones



Use to charge tablets



Charge the Powerpod itself by AC power adapter



Charge the Powerpod itself by a USB Port

Power Level Indicators	LED1-LED4 are on	LED1-LED3 are on	LED1-LED2 are on	LED1 is on	LED1 is flashing
Remaining Power Level	100%~75%	75%~50%	50%~25%	25%~10%	10%~0%

Safety Instructions

- Do not throw the Powerpod into fire or try to heat it. In such situations it might burn, explode or release toxic gas
- Do not connect the micro USB input and USB output ports with a single cable.
- Do not try to open the Powerpod by yourself or break it.
- Do not put the Powerpod in water or make it wet.
- Do not use Powerpod if you notice it is leaking, heating itself, out of shape, smelling or any other abnormal phenomenon.
- Do not use the Powerpod at higher temperature than 60 °C. The recommended ambient temperature is between 15 °C and 25 °C.

Storage and Maintenance

- If you will not use the Powerpod for a long time, please at least once a year fully charge it, then discharge it by some outer devices, then recharge it to half capacity and then keep it in a cool and dry place.
- It is recommended to perform a complete charging and discharging every 3 months so as to ensure the best status of the battery cells inside.

Support

For support please visit our website at www.powerpod.net or email us at support@powerpod.net