



PRO BUSINESS RADIO PX500 6 Pack Bundle with Gang Charger

PX500-BCH6

Radio

Up to 250,000 sq ft / 20 Floor Range

Provides extended signal range with 2662 channel combinations.

22 Preset Channels

Channels are preset with Privacy codes to minimize unwanted interference from others.

VOX

Voice-activated transmission frees hands for other tasks.

Long Runtime

Can continue to use 12 hours (90% Standby / 5% Talk / 5% Listen).

180° Swivel Holster

Fast Charging

Charges fully in 5 hours.

Gang Charger

Convenient & efficient charging

Can charge 6 radios (PX500) simultaneously.

Simple to use

Each pocket includes an LED indicator showing charge status of each radio at a glance.

Fast charging

Charges fully in 5 hours.

Adaptor with 6 foot (1.8M) cable



Nothing Comes Close to a Cobra®

www.cobrawalkietalkie.com

PX500-BCH6

Features

Benefits

Radio	
UHF/FM	Ultra-clear long distance reception.
250,000 sq ft / 20 Floor Range	Up to 250,000 sq ft / 20 Floor range. (Range will vary depending on terrain and conditions.)
22 Preset Channels	22 channels have been preset with privacy codes to minimize unwanted interference from others.
121 Privacy Codes	38 CTCSS (Continuous Tone Coded Squelch System) codes and 83 DCS (Digitally Coded Squelch) codes provide a total of 121 privacy codes. 2662 privacy combinations are possible when the 22 channels are combined with the 121 privacy codes.
VOX (Voice Activated Transmission)	User's voice is detected and the radio transmits without the need to press any buttons, freeing the user's hands for other tasks. 5 VOX sensitivity levels allow user to select at which point the radio will detect their voice.
Call Alert	Provides an easily recognizable alert for incoming calls.
Roger Beep Tone	Confirmation tone indicates the completion of the user's transmission, and signals others it is clear to talk.
Key Lock	When activated, provides key pad security eliminating accidental channel changes.
Auto Squelch	Automatically shuts off weak transmissions or unwanted noise due to terrain or range constraints.
LCD Display	Easy to view display provides the radio's status at a glance.
Speaker/Microphone/Jack	Allows use of wall charger, or earphone speaker/microphones (not included) for "hands-free" operation.
180° Swivel Holster	Secures your microTALK® radio while on the go.
No Licence or Service Fess	High quality band frequencies with no fees.
Volume Knob	Allow user to adjust any volume level easily and promptly.
Gang Charger	
6 charger dock	Allows you to charge 6 radios (PX500) simultaneously.
LED indicator	Shows charge status of each battery at a glance.
Adaptor with 6 foot (1.8M) cable	Enables flexible and easy placement

Unit Specifications - General

Radio		Charger		Package (Brown Box) Dimension	TBA
Unit Dimension	147.4mm x 54.6mm x 45.6mm (5.80" x 2.15" x 1.79")	Unit Dimension	52mm x 379mm x 109mm (2.05" x 14.92" x 4.29")	Package (Brown Box) Weight	TBA
Unit Weight	172g. (6.07 oz.) without batteries	Unit Weight	544g. (19.19oz.)	Master Pack Bar Code	10810026630122
QTY in the Pack	6	QTY in the Pack	1	Master Package Dimension	TBA
RF Output	1W	Input	100 - 240V ~ 50/60 Hz 0.6A Adaptor with 6 foot (1.8M) cable	Master Pack Weight	TBA
Batteries	1 pack of 1000mAH Li-ion Rechargeable Battery per radio	SKU#	PX500-BCH6	Master Pack Qty	4
22 Channels with Default Privacy Code		UPC	810026630125	*Specifications subject to change without notice* *All dimensions (H x W x D)*	

Channel	Privacy Code		Channel	Privacy Code	
	Type	Number		Type	Number
1	CTCSS	1	12	DCS	77
2	CTCSS	11	13	CTCSS	1
3	CTCSS	22	14	CTCSS	11
4	CTCSS	33	15	CTCSS	22
5	DCS	1	16	CTCSS	33
6	DCS	11	17	DCS	1
7	DCS	22	18	DCS	11
8	DCS	33	19	DCS	22
9	DCS	44	20	DCS	33
10	DCS	55	21	DCS	44
11	DCS	66	22	DCS	55

What is Included:



Cobra®, microTALK®, Nothing Comes Close to a Cobra®, and the snake design are registered trademarks of Cobra Electronics Corporation, USA.

Cobra Electronics Corporation™ is a trademark of Cobra Electronics Corporation, USA.

©2019 Altis Global Limited, Atlanta, GA USA



* Packaging is made from recyclable materials.

Nothing Comes Close to a Cobra®