

Flash Programmer – Two Socket

Part No. 01LP3

LEAPER-3C is specially designed for FLASH series, integrating powerful hardware and software to perform high quality . It is the best choice to program FLASH series device. The most attraction of the LEAPER-3C is following 4T products policy, i.e. Light, Thin, Short, Tiny. Con-cerning the concept of environmental protection, the LEAPER-3C avoids unnecessary over-package. LEAP is doing her responsibility for the earth.

FEATURES

- Small, portable, light & usable with batteries
- Stand-Alone FLASH programmer
- Only one source is needed to copy with.
- Two operation modes:stand-alone&PC mode
- Support Windows 95/98/NT/2000/ME/XP

STAND-ALONE MODE

- 5 Function keys
 - Functions
 - Type
 - Blank check
 - Verify & check sum
 - Program
- IC parameters are adjustable such as programming algorithm, Vpp voltage, and impulse width.

PC BASED MODE

- Connect with PC by USB port to transmit data and execute functions such as :
Type/ Read/ Blank Check/ Program/ Verify/ Erase/ Disk/ Help/ Process/ Parameter
- C parameters are adjustable such as programming algorithm, Vpp voltage, and impulse width.
- File formats supported:
Binary and machine code, Intel HEX ,
Motorola HEX

PHYSICAL & ENVIRONMENTAL SPECIFICATION

- Display: LCD with 16 x 2 characters
- Dimension 16cm x 11cm x 4.5cm
- Weight 0.5Kgs
- Temperature +5°C to +45°C
- Humidity up to 90%
non-condensing
- Altitude: up to 5000m

SAFETY STANDARD

Meet CE requirement

STANDARD ACCESSORIES

- Main unit
- CD ROM (installation program and user's manual are included)
- USB cable
- 12V/500mA power adaptor

OPTIONAL ACCESSORIES

- Various PLCC, TSOP, VSOP converters



SUPPORTED DEVICES

EPROM
27C64- 27C080
EEPROM
28C256-28C040
FLASH EPROM
29C256-29C040
29EE/LE512-29EE/LE020
28F256-28F020A
28SF/VF 040
29F010-29F040
29F001-29F002
39SF/VF512-39SF/VF040
49F512-49BF040
49F/LV001-49F/LV002