




LP 32

USB to DMX interface



Compatible with the affordable LED Player software, Chromateq's most economical USB to DMX controller is a perfect fit for projects that only require a few channels of DMX control, for testing and troubleshooting, or as a promotional package for the novice lighting programmer.



10th
YEAR
ANNIVERSARY

↓
FREE

DESIGNED & DEVELOPED
IN FRANCE

1
YEAR
WARRANTY

 **CHROMATEQ**



HARDWARE Options

DMX Output	32 Output channels PC and 128 Out Stand Alone
Zone	1 Zone, play 1 scene/sequence at time in Stand Alone
Memory	Internal memory (40 KB, 300 to 55 DMX step capacity)
Triggers (Stand Alone)	16-bit and fine channel management Cross Fade time between scenes Default start scene when power up
Power	5V DC (USB) - 0.1A, 0.2W, High Voltage Protection
Dimension	H : 40mm(1.57in) / W : 31mm(1.22in) / D : 75mm (2.96in)
Housing	Strong Aluminum
I/O Connectors	Mini USB 2.0, 3 pin XLR (XLR5 optional)
Operating Temperature	-40 to +85 C°
IP Rating	IP40
Certifications	CE, LVD, RoHS
International Warranty	1 year



SOFTWARE Options

LED Player	32 DMX Outputs, 32 scenes
Pro DMX	32 DMX Outputs, 32 scenes
Studio DMX	3D viewer in real time (Full mode)
Wi-Light 2 APP	Mobile software control (Android, iOS)
System Compatibility	Windows, iOS, Linux

FREE SOFTWARE Download and Update



2010 - 2021 Chromateq SARL
Chromateq - All rights reserved

191 Allée de Lauzard
34980 St Gély du Fesc, FRANCE
Web: www.chromateq.com
Email: info@chromateq.com
Phone: +33 952210755
Wechat: Chromateq
WhatsApp: +8613422062209
QQ: 2908265661

Software & App download:

Software package download: <https://www.chromateq.com>
Wi Light 2 app download (iOS): <https://apps.apple.com/us/app/wi-light-2/id1523046687?l=fr>
Wi Light 2 app download (Android): <https://play.google.com/store/apps/details?id=com.chromateq.wilight2>

PC minimum configuration:
Windows / Mac OS / Linux (Device)
2Ghz CPU, 8 Gb RAM
2Gb RAM graphic card
500 Mb disk
1 USB port (Device)
1 Ethernet Port (for Art-Net & sACN)



www.chromateq.com
Contact • Support • Download