

AIR400-12P / AIR600-12P
AIR400-PC-12P / AIR600-PC-12P
AIR400S-12P / AIR600S-12P
AIR400S-PC-12P / AIR600S-PC-12P

Airlite / Airlite Stream Path Light 12v INSTRUCTIONS



WARNINGS



PLEASE READ THESE INSTRUCTIONS CAREFULLY BEFORE COMMENCING ANY WORK

- This is a Class 3 product (Low Voltage) – no earth required.
- **12V TRANSFORMER MAY BE REQUIRED – sold separately**
- This unit must be fitted by a competent person – if in doubt consult a qualified electrician.
- Install in accordance with IEE wiring regulations and current Building Regulations.
- To prevent electrocution, switch off mains supply before installing or maintaining this fitting. Ensure other persons cannot restore the electrical supply without your knowledge.
- This light fitting should be connected to a circuit with a 30Ma RCD fitted.
- If replacing an existing fitting, make a careful note of the connections.
- When changing the bulb, always switch off at the mains & allow the bulb to cool before handling – **LAMP WILL GET HOT WHEN IN USE.**
- All connections should be made as watertight as possible to avoid electrical shortage.
- Always use the correct type & wattage of bulb. Never exceed the wattage stated.
- The unit may get warm whilst on for a period of time.
- **The head of the product is heavy (up to 3kg) – please handle with care**

Materials: Anodised Aluminium & Solid Crystal Glass

Voltage: 12v – Low Voltage

Max. Wattage: 35W

Lamp Fitting: MR16

Recommended Lamp: LED

IP Rating: IP65

Product Height: 400mm or 600mm

Sensor: Photocell (Dusk to Dawn) OPTIONAL



**3 YEAR
GUARANTEE**

*see website for
more details*

Producer Registration Number:

WEE/KC3440XY

RETURNS – Please contact us by phone or email

Lumena Lights Ltd
Centre 33 Long March
Daventry
Northants
NN11 4NR

Tel: +44 1327 871161
Fax: 0800 066 4410
Email: sales@lumenalights.com

Full product range & more information:

www.lumenalights.com



INSTALLATION:

- A length of 12v 2 core rubber cable is supplied with a VERSA 2 pin male plug (H05RN-F – may vary).
- Push the plug firmly into the female adaptor of the Transformer or splitter.
- Screw the attached threaded cap to the female adaptor to create a secure connection.
- If a splitter is used, ensure a waterproof cap is used to cover any unused terminals.
- Unscrew the head carefully and install MR16 bulb into the bulb holder via the guide clip (push).
- Carefully place the rubber seal between the body and head to ensure a waterproof seal and screw on head securely.

NOTES:

- To ease with head / body assembly, a small amount of oil such as '3 in 1' can be applied to the neck thread.
- If the head is accidentally cross-threaded when securing to the body, turn anti-clockwise and try again – it should then screw on easily.
- Product base is fixed to the main part of the light. 4 x Anchor bolts can be used to fix the product to the relevant surface (not supplied).
- The rubber seal supplied must be installed between the head and the body and **MUST NOT** be twisted to ensure a waterproof connection.
- Photocell versions – photocell is factory pre-set and cannot be changed.
- **The head of the product is heavy (up to 3kg) – handle with care**

**Male 2 Pin Plug & Play Adaptor
(supplied)**



Female 2 Pin Plug & Play Adaptor



CLEANING:

Occasional cleaning and care is recommended for this product. Please refer to our website for the best way to clean different materials.