




**PROTEKT<sup>®</sup> DIGITAL  
PATIENT LIFT SCALE  
with UNIVERSAL BRACKET KIT**

**MODEL: 30300**

**For use with Proactive Patient Lift Models:  
33500/33600/33400P**



**Owner's Manual**

270 Washington Street  
Mount Vernon, NY 10553

Tel: 855-237-7622

[www.proactivemedical.com](http://www.proactivemedical.com)

# Content

1. Safety Guide .....	1
2. Features .....	1
3. Specifications .....	2
4. Capacity .....	2
5. Display & Keys .....	3
Scale Keys .....	3
Indicators .....	3
Message .....	4
6. Operations .....	4
Power On/Off .....	4
Zero .....	4
Tare In/Out .....	5
Lock/Unlock .....	5
Unit Switch .....	5
7. User Setup .....	5
Auto-Off Timing .....	5
Backlight Brightness .....	6
Idle Mode Timing .....	6
8. Battery Maintenance .....	7
9. Troubleshooting .....	7

Please read this manual carefully before using.

# 1. Safety Guide

**For good scale performance and precise measurement, be careful with daily operation and maintenance.**

Do NOT overload scale. Make sure the patient does not weigh more than 660 lbs as this will damage loadcell and void warranty.

Inspect shackle and Sling Bar/Cradle before using. Check clips, pins and screws regularly.

Check battery frequently. When scale runs out of power, replace the dead batteries with new ones.

Rotate load rather than scale if needed.

Do NOT get the scale wet or get near water.

Store the Lift scale in a dry and well-ventilated room. Do NOT place scale on the ground or drop it.

Do NOT attempt to repair scale yourself.

# 2. Features

**This scale is a combination of sound and proven mechanical design, with today's most advanced electronics to provide a superb feature set. It is versatile, reliable, accurate and easy to operate.**

- Superb Quality.** Strictly in accordance with CE directives.
- Safety.** Aluminum-casting case, SS shackle, dedicated weighing loadcell for safety installation.
- Strong Reliability.** Cutting-edge technology, quality integrated circuit for high performance and long-time stability.
- Broad Applicability.** The scales are well-suited for hospitals, home care, nursing homes, retirement homes and rehabilitation centers.
- Complete Function.** Resolution switch, unit conversion, auto power-off, battery inspection, etc.

### 3. Specifications




Accuracy	OIML R76
Tare Range	100% F.S.
Zero Range	4% F.S.
Stable Time	≤10sec
Overload	100% F.S. + 9e
Safety Load	120% F.S.
Ultimate Load	400% F.S.
Battery	3*AA 1.5V batteries.
Battery Life	≥65hour (tested by dedicated batteries, backlight level 3, always lit)
Display	22mm/11mm HTN LCD with backlight
Op. Temp.	-10°C ~ +40°C
Op. Humidity	20°C ≤90%

### 4. Weight Capacity








Model	Max. Cap.	Min. Cap.	Res.	Division
30300	660 lbs	4.4lbs	0.2lbs	3,000

## 5. Display & Keys

### Scale Keys

Key	Name	Function
	On/Off	Short pressing: Cancel & return to weighing mode Long pressing: Power-on / Power-off
	Tare	Short pressing: Tare in/out; Increase digit Long pressing: Zero; Move digit
	Hold	Short pressing: Lock/unlock; Confirm & next Long pressing: Unit Switch; Input / cancel decimal point

### Indicators


LED	Name	Note
	Stable	shown when weight is stable
	Zero	shown when weight is at zero
	Tared	shown when scale is tared
	Hold	shown when scale is locked
	lb	shown when unit is lb
	kg	shown when unit is kg
	UN	shown when unit is User Unit

## Message

Message	Stand for	Note
-----		detect weight
SETUP	SETUP	User Setup Menu
bAt99	Battery	battery life percentage
End	END	save and exit
off	OFF	power off
over	Overload	overloading
Err	Error	invalid operation


## 6. Operations

### Power On/Off

- ✓ Press  for 1 time to power-on scale. Scale perform initialization and power-on test, **88888** shows twice, then capacity


**660** shows, battery life percentage **bAt99** shows, weight detection **-----** shows and then auto zero.

- ↪ For information about Auto-Zero, refer to Scale Configuration in Technical Manual.

- ✓ Press  for 1 time to power-off scale. Battery life percentage **bAt99** shows, off message **off** shows, and then cut off power.

- ↪ When 3 batteries voltage is lower than 3.2V, scale will auto power-off itself. Please replace the dead batteries with new ones.

### Zero



- ✓ Press  for 1 time to zero. **Z** shows.

If load is in motion, or tared, or out of Manual-Zero Range,



**Err** shows.

↪ For information about Manual-Zero Range, refer to Scale Configuration in Technical Manual.


### Tare In/Out

- ✓ In gross mode, press  to tare in. **T** shows.  
If load is in motion, or negative, or out of Tare Range, **Err** shows.  
Tare will reduce the apparent overload range of scale. For example, if a 500\*0.2kg scale has a 100kg container as its tare, the scale will overload at a new weight of 401.8kg (500 – 100 + additional 9 divisions).
- ✓ In net mode, press  to tare out. **T** disappears.



### Lock/Unlock

- ✓ Press  to lock screen. **H** shows.
- ✓ Press  to unlock screen. **H** disappears.



### Unit Switch

- ✓ Press  for 1 time to switch unit in between kg, lb, and User Unit.  
When unit is kg, **KG** shows. When unit is lb, **LB** shows.  
When unit is User unit, **UN** shows.  
For more information about User Unit, refer to Scale Configuration in Technical Manual.

## 7. User Setup

- ✓ Press  and  at the same time for 1 time to enter User Setup menu. **SETUP** shows.

### Auto-Off Timing

- ✓ Press  to enter Auto-Off Timing. **off--** shows.
- ✓ Press  to change timing value.

↙ Auto-Off Timing can be set to: **0** (disabled), **5** (5min), **10** (10min), **15** (15min), **30** (30min), **60** (60min). It is disabled by default.

Auto-Off function maximizes scale's battery life against people's carelessness not to power off scale when it's not working.

Auto-Off starts countdown timer when there's no action or load is stable. Any key pressing or motion in load restarts countdown timer.

## Backlight Brightness

☑ Press  to enter Backlight Brightness. **br** shows.

☑ Press  to change brightness value.

↙ Backlight Brightness can be set to: **off** (disabled), **1** (dim), **2** (normal), **3** (bright).

Dim backlight brightness saves battery power dramatically.

## Idle Mode Timing

☑ Press  to enter Idle Mode Timing. **IDL--** shows.

☑ Press  to change timing value.

↙ Idle Mode Timing can be set to: **0** (disabled), **5** (5sec), **10** (10sec), **15** (15sec), **30** (30sec), **60** (60sec). It is 30sec by default.

To maximize battery life, scale automatically enters Idle Mode, when there's no action or the load is stable. In Idle Mode, scale works in low-power consumption status. Any key pressing or motion in load wakes up scale from Idle Mode.

☑ Press  to exit User Setup.



## 8. Battery Maintenance

To maximize battery life, please note the following battery maintenance guide.

This scale is powered by a 3 AA 1.5V batteries.

Battery house can be opened by screwing off 2 screws.

Depending on backlight brightness and idle mode setting, normally, battery works over 65 hours.


In order to conserve battery life, enable Auto-Off and Idle Mode, dim backlight brightness.

To obtain maximum service life, battery should be stored between -20°C (-4°F) and +50°C (122°F). Stored batteries should be recharged every three months or replaced.

When 3 batteries voltage is lower than 3.2V, scale will auto power-off itself. Please replace the dead batteries with new ones.

## 9. Troubleshooting

Simple problems can be resolved as below listed solution.

Symptom	Possible Cause	Suggested Solution
not power-on after  is pressed	discharged / defective battery	check battery and replace
	defective On/Off key	press harder and keep pressing for 2s
	defective power cable	open front panel, check power cable
	defective mainboard	contact representative

backlight flashes	discharged battery	replace battery
no action taken after key pressed	scale is disturbed	re-plug power cable
	defective key	contact representative
weight reading not stable	load in motion	keep load stable
	weak Anti-Motion	change Anti-Motion level
	damped loadcell or mainboard	dry loadcell or mainboard
	defective mainboard	contact representative
weight reading not zero when no load	discharged battery	replace battery
	load-cell stressed too long	hang scale in storage
	loadcell drifts	contact representative
large error in weight reading	scale not zeroed before applying load	Manual Zero scale before loading
	wrong unit	switch to correct unit
	scale requires calibration	calibrate scale
	defective loadcell or mainboard	contact representative

COPYRIGHT All rights reserved. Reproduction or use, without expressed written permission, of editorial or pictorial content, in any manner, is prohibited. No patent liability is assumed with respect to the use of the information contained herein.

DISCLAIMER While every precaution has been taken in the preparation of this manual, the Seller assumes no responsibility for errors or omissions. Neither is any liability assumed for damages resulting from use of the information contained herein. All instructions and diagrams have been checked for accuracy and ease of application; however, success and safety in working with tools depend to a great extent upon the individual accuracy, skill and caution. For this reason, the Seller is not able to guarantee the result of any procedure contained herein. Nor can they assume responsibility for any damage to property or injury to persons occasioned from the procedures. Persons engaging the procedures do so entirely at their own risk.

#### STATEMENT OF LIMITED WARRANTY

The Protekt<sup>®</sup> Digital Patient Lift Scale you purchased is guaranteed to be free from defects in material and workmanship under normal use and service. The warranty period for this product is 2 Years from the date of purchase by the original purchaser. This warranty shall be voided upon transfer of ownership of this product. Proactive Medical agrees to repair or replace this product, at our discretion and at no charge, within the warranty period provided and that Proactive Medical consents the

unit is defective. The repaired or replacement unit shall be warranted for a period equal to the balance of the defective unit's warranty period.

**NOTE:**

To ensure the best service to our customers, Proactive Medical requires the following information to be included with the returned unit:

1. Model Name/Number and Serial Number on the packaging.
2. Proof of purchase, i.e. a copy of the original invoice.
3. A Return Authorization number (RA#) obtained by calling Authorized dealer/distributor prior to the return of the product. The RA# must be clearly indicated on the outside of the packaging.
4. A detailed description of the problem and its symptoms on a note.

This warranty shall not apply to any product which has been repaired or altered in any way so as, in our judgment, to affect its functionality and durability, nor to any product subject to abuse, misuse, negligence or accident, improper maintenance, improper installation, nor to any product used with other parts, components and/or accessories with quality and/or specifications not compatible with this product. This warranty does not cover products that have been impaired by occurrences considered Acts of God over which authorized dealer has no control. This warranty shall also be voided if any required periodic maintenance, if applicable, has not been properly performed on this product.

This warranty and the aforementioned remedies presented are exclusive and in lieu of all other express or implied warranties. No other representations or claims shall be binding or obligate authorized dealer in any way. Any warranty applicable to this product is limited to the aforementioned period indicated. In no event shall authorized dealer be liable for any special, incidental, or consequential damages; loss of revenue; or cost of replacement goods; resulting from the use or malfunction of this product to the associated equipment on which and with which it is used. This warranty gives specific legal rights and you may be entitled to other rights that vary from state to state.