


MEGA^{LITE}

MEMO^{SPLITTER} A8



Architectural

Product Description:

The MEMO Splitter A8 is designed for architectural installation applications and is the ultimate DMX signal amplifier, distributor, and supports bidirectional RDM signal. This powerful device empowers lighting professionals to split a single universe signal into eight separate outputs while boosting its signal strength, ensuring communication between controllers and DMX lighting fixtures.

8 Outputs

This versatile device features one input and eight RJ45 and eight 3-port screw terminal outputs, allowing you to split and boost your DMX signal for extensive cable runs.

RDM

Benefit from the added advantage of Remote Device Management (RDM) signal regeneration. The Memo Splitter A8 receives and regenerates RDM signals, allowing you to maintain constant control and monitoring of your DMX lighting fixtures.

Isolation

Benefit from enhanced reliability with electronic isolation between DMX connections. This feature protects your equipment from potential electrical interference and ensures smooth signal distribution.

Mechanical Specifications

Input DMX Connections:	In and Thru RJ45 & In and Thru 3 Port Screw Terminal
Output DMX Connectors:	8 Output RJ45 & 8 Output 3 Pin Screw Terminal (Can Only Use One Type At A Time)
Power Connection:	PowerCon Type (PowerCon to Nema 5-15 Cable Included)
Fastening System:	1U Rack Mountable Front or Back & Wall Mountable (Hardware Included)


Electrical Specifications

Outputs:	Eight (8)
Input Isolation:	Yes
RDM Signal:	Boost, Repeat Cleans and Regenerates RDM Signal Prevents Reflection
Signal Lines:	LED Signal Indicators
Display:	RDM E 1.20
Compliant:	.6 Amps @ 110V AC 60Hz
Power Consumption:	90-120-AC 60Hz
Power Input:	

Control System

RDM:	Yes
DMX-512:	Yes
Universes:	Single Universe

RJ45 Connection



Pin	Connection
1	GND
2	GND
3	Not Used
4	Not Used
5	Not Used
6	Not Used
7	Signal -
8	Signal +

3 Pin Terminal Screw

Input




Output



Pin	Connection
1	GND
2	Signal -
3	Signal +

Size and Weight



Fixture Size:	19" x 7.25" x 1.75"
Fixture Weight:	6 lbs
Packaged Size:	21.6" x 9.5" x 3"
Packaged Weight:	7 lbs

Included Items

Part Number:	MEMO Splitter A8 MC1070
Part Number:	Input Green Screw Terminals (3 Position) #MC1070-CON-GRE
Part Number:	Output Orange Screw Terminals (3 Position) #MC1070-CON-ORA
Part Number:	Removable Rear Ears & Wall Mount Hardware #MC1060-HAR-RAC

Customer Service

MEGA-Lite has a customer support line to provide set-up help and answer any questions should you encounter a problem. Please visit our website for any other related technical documents. For service-related issues, please contact our service department.

Operating Hours:	Monday - Friday 9AM - 6PM CST
Phone:	(210) 684-2600
Email:	Service@mega.lighting



18668 Highway 16N
Helotes, TX 78023
Phone (210)684-2600 / Fax (210)855-6279
www.mega.lighting / info@mega.lighting