



Pro Intercom LLC ©

Intercom for Sound, Lighting and Production Professionals

Blazon 4 Xenon Strobe Light



- ✓ Performance
- ✓ Durability
- ✓ Value
- ✓ Compatibility

Performance: Blazon 4 is triggered by the same voltage which lights the normal signal lamps in the intercom system. Whenever any signal lamp button on any station in the same circuit is pressed, the Blazon 4 will be activated. The xenon lamp is permanently connected. Circuitry is provided to sustain the Blazon 4 for 4 seconds after being triggered. The xenon lamp has a flash rate of 2Hz, providing 8 flashes per cycle.

The Blazon 4 is connected to the headset intercom system in the same manner as a belt pack. It has two 3-pin XLR connectors on the rear panel. By convention (to differentiate from microphone inputs) the female connector is designated as input. The male connector is provided for looping onwards to the next station in the system. Reversing these connections will not affect operation.

Blazon 4 is powered by the intercom power supply and requires no batteries or other external power source. In its ready mode it draws only 21.1mA; with the strobe active, 120mA. When calculating power supply requirements, you may consider the Blazon 4 as the approximate equivalent of 3 or 4 belt packs.

Durability: The ribbed, extruded aluminum case; glass-filled nylon end bezels; internal support system for the PC board, and; best quality XLR-type connectors, all contribute to the Blazon 4's ability to withstand rough usage.

Value: The comparatively low price of the Blazon 4 is made possible by the minimized assembly cost resulting from simplicity of construction.

Compatibility: Blazon 4 is compatible with Clear-Com® and other lesser known (unbalanced 200) party-line headset intercom systems.

Technical specifications: (Subject to change without notice)

Supply voltage: 24 ~ 30 VDC nominal

Switch-on voltage: 8 Volts minimum

Switch-off voltage: 5 Volts maximum

Switch-on time: 75 milliseconds

Switch-off time: 4 seconds

Flash rate: 2Hz Flash power: 0.75 joules

Input impedance: 1 Meg

Power consumption: Ready - 21.1mA

Strobe only - 68 mA

Size: 3.70x4.30x5.80 in. (93.98x109.22x147.32 mm)

Weight 20oz. (0.567Kg)

Pro Intercom LLC

PO Box 7035 Algonquin Illinois 60102-7035

Phone: +1 (815) 680-5205 Orders and Tech support: (888) 320-5928 Fax: +1 (815) 526-8689

support@prointercomllc.com Skype: intercom4pros

Printed in U.S.A.

Rev.3_01.13