

CARNAGE TOOLS™

RECHARGEABLE LED WORK LIGHT

USER MANUAL

CT1KWL



EN OPERATING INSTRUCTIONS CT1KWL



Thank you for choosing the CT1KWL Work Light from **CARNAGE TOOLS™**. Please follow all the warnings and instructions within this User Manual.

TECHNICAL DATA

Light Source	high power COB LED – Main light high power SMD LED – Top light
Luminous Power	1000 lm – Main light High mode 500 lm – Main light Medium mode 250 lm – Main light Low mode 170 lm – Top light
Operating time	up to 1.5 h – Main light High mode up to 3 h – Main light Medium mode up to 7 h – Main light Low mode up to 5.5 h – Top light
Battery Specification	Li-Ion 3.7 V, 3350 mAh, 12.395 Wh
Charging Time	5 hrs
Charging Input	DC 5V 1A
Dust & Water Resistance	IP65
Impact Rating	IK 09
Operating Temperature	15 °F to 105 °F
Storage Temperature	15 °F to 105 °F

WARNING

- Opening the light will void warranty.
- Do not look directly into the light emitting lamp - Risk of eye injuries!
- Do not operate in direct sun light or extreme temperature conditions.
- Operating temperature, 15 °F to 105 °F.
- Keep away from children! Children should be supervised in order to ensure that they do not play with the device!
- Do not place the light face down while on for long periods of time as this will cause damage to surface and possible fire.
- Power Input only can be 5V-1A UL/ETL approved adapter. Do not use different power input adapter. This may cause damage to the product and may cause fire.

OPERATING & CHARGING PROCEDURE

- CT1KWL Operating mode as below
 - Press the Power Button first time, top light switch on.
 - Press the Power Button second time, main light switch to Low mode.
 - Press the Power Button third time, main light switch to Medium mode.
 - Press the Power Button fourth time, main light switch to High mode.
 - Press the Power Button fifth time, all power off.
- Switch lamp off and connect with USB charger during charging.
- The battery indicator will blink during charging.
- All the battery indicator lights will stay lit after finished charging.
- If the battery indicator did not light up, please remove the charger and try again.
- Always only use the charger recommended by **CARNAGE TOOLS™** to charge the lamp. The use of a NON-recommended charger can lead to a fire and destroy the lamp.
- Before using the hand lamp for the first time, charge it for 4-5 hours.
- Fully charge the hand lamp before it is stored for a long period.

ⓘ SAFETY INSTRUCTIONS

- Do not use the device if there is damage to the housing, plug or cable. Contact **CARNAGE TOOLS™** Customer Service.
- Clean hand lamp only when the main plug is removed from the main power.
- There is a risk of short-circuit. Repairs on the device may only be carried out by **CARNAGE TOOLS™** Technical Service.
- Protect the battery against heat, e. g., against continuous intense sunlight, fire, water, and moisture. Danger of explosion.
- If the battery is damaged or not used correctly, fluids can leak from the battery. Avoid contact with these. Leaking battery fluids can lead to skin irritation or burns. Rinse off with water if you should come into contact. If the fluid gets into your eyes, make sure you get medical help.

🌍 Environmental Protection

- The device should not be discarded in the normal household waste under any circumstances.
- Dispose of the device via an authorized disposal center or your communal waste disposal facility. Observe the current applicable regulations. Contact your waste disposal facility in the event of any doubt. Dispose of all packaging materials via an environmentally friendly disposal facility. Rechargeable batteries must not be disposed of in the household waste.



WARRANTY

- The device has a one years WARRANTY against faulty workmanship or materials. The guarantee does not apply to damage to the device arising through a failure to comply with the operating instructions.

CARNAGE TOOLS™

KILLING THE COMPETITION

Contact Info:

Carnage Tools
4833 Berewick Town Center Drive
Suite E192
Charlotte, NC. 28278
Ph: 888-4-CARNAGE
www.carnagetools.com