

29-31 Richland St. Kingsgrove. Sydney NSW 2208 Australia

Phone: 02 9554 9600 | Fax: 02 9554 9433

enquiries@domuslighting.com | www.domuslighting.com

Installation Manual

MONDO-300/400

	-	
Order Code	Product Code	Description
20870	MONDO-300-RND-W-WW	20W LED Slim Ceiling Light, Warm White 3000K
20872	MONDO-300-RND-W-W	20W LED Slim Ceiling Light, White 5000K
20876	MONDO-400-RND-W-WW	30W LED Slim Ceiling Light, Warm White 3000K
20878	MONDO-400-RND-W-W	30W LED Slim Ceiling Light, White 5000K

Thank you for purchasing your new LED MONDO-300/400, Please take the time to read and understand the instruction sheet below. Failure to do so may void warranty.


Specifications


MONDO-300


Voltage:	240V	Lumen (±5%):	Warm White 3000K - 1570lm	Dimmable:	Yes
			White 5000K - 1630lm		
Power:	20W	Beam Angle:	120°	Operating Temp:	-20°C~45°C
IP Rating:	44	CCT:	3000K - 5000K	Power Factor:	≥0.9
CRI:	≥80	Lifespan:	50,000hrs		


MONDO-400

Voltage:	240V	Lumen (±5%):	Warm White 3000K - 2400lm	Dimmable:	Yes
			White 5000K - 2430lm		
Power:	30W	Beam Angle:	120°	Operating Temp:	-20°C~45°C
IP Rating:	44	CCT:	3000K - 5000K	Power Factor:	≥0.9
CRI:	≥80	Lifespan:	50,000hrs		










Aim the buckle at the gap of installation bracket.



4. Aim the buckle at the the gap of installation bracket and push it upward, adjust the lamp's position clockwise and counter-clockwise to fit the lamp into the bracket, then rotate the lamp clockwise until it is fixed well.







5. Connect the lamp to the mains supply after finish the installation.

Note: -The lamp must be installed by professional electrician

-Ensure the power supply is switched off before fitting this product

- -Do not touch the lamp when in use
- -Keep away from hot steam and corrosive gas