

Mirror light with shaver socket

MODEL: RCTM2T8

Installation:

1. Choose the location for your mirror light complying with the conditions listed opposite.
2. Lay the fitting flat and remove the four screws that retain the mirror (two each side).
3. Lift the mirror off of the fitting and store safely.
4. Using the metal case as a template, mark the position of the fixing holes. Laying a spirit level across the top of the metal case will help ensure that your mirror is installed level.
5. Prepare the fixing holes as appropriate to your mounting surface.
6. Pierce the rubber grommet in the cable entry hole that you intend to use. Do not make the hole too large, the rubber grommet must make a watertight seal around the supply cable.
7. Thread the supply cable through the pierced grommet.
8. Secure the metal case to the wall using the fixings supplied. If the fixings supplied are not appropriate to your installation, use suitable alternatives.
9. Make the electrical connections according to the colour code opposite.
10. Re-fit the plastic cover over the terminals and transformer.
11. Fit the fluorescent tubes by slotting into the lampholders and turning through approx 90° or until they click softly into position.
12. Check that the soft gasket is correctly positioned around the facing edge of the metal case.
13. Replace the mirror and secure in position using the four screws removed previously. Press firmly on the mirror to ensure a tight fit against the gasket before tightening screws.
14. Restore the power and switch on.

Lamp replacement:

1. Switch off the electricity at the mains.
2. Remove the four retaining screws (see diagram inside) and lift off the mirror.
3. Remove and replace tube(s). Fit the fluorescent tubes by slotting into the lampholders and turning through approx 90° or until they click softly into position.
4. Check that the soft gasket is correctly positioned around the facing edge of the metal case.
5. Replace the mirror and secure in position using the four screws removed previously. Press firmly on the mirror to ensure a tight fit against the gasket and tighten the screws. Restore the power and switch on.

Replacement lamp type:

Wattage: 15 W x 2

Type: T8 fluorescent tube. Warm White colour.

Please read these instructions before installing your new fitting. Please retain for future reference

1. Switch off the mains before commencing installation and remove the appropriate circuit fuse.
2. This fitting contains an isolating transformer rated at 20W maximum and is only intended for use with electric shavers. It is possible to connect other devices to the socket outlet such as chargers for electric toothbrushes provided they are fitted with the correct plug. Use of the socket to power equipment requiring greater than 20W will cause the transformer to overheat and stop working altogether. Please refer to the manufacturer's instructions supplied with your appliance to determine whether it is suitable for use in the location where you have installed your shaver light and that the power consumption is less than 20W.
3. The switch in your fitting turns the light on and off. The sockets are permanently live.
4. When using the shaver socket, ensure that the correct socket is used according to the working voltage of your appliance. Connecting your appliance to the wrong socket could cause permanent damage to your appliance, your fitting or both.
5. Suitable for indoor use only.
6. This fitting is suitable for use in bathrooms in Zone 2 or 3 or the safety or outside zone. This fitting must not be installed in zones 0, 1 see diagram opposite.
7. This product is suitable for installation on surfaces with normal flammability (indicated by the "F" in a triangle) e.g. wood, plasterboard, masonry. It is not suitable for use on highly flammable surfaces (e.g. polystyrene, textiles).
8. Before making fixing hole(s), check that there are no obstructions hidden beneath the mounting surface such as pipes or cables.
9. The chosen location of your new fitting should allow for the product to be securely mounted and safely connected to the mains supply (lighting circuit).
10. The fitting, especially the shaver socket, should be placed where it cannot be splashed.
11. This product is designed for permanent connection to fixed wiring: this should be either a suitable lighting circuit (protected with a 5 or 6 Amp MCB or fuse) or a fused spur (with a 3 Amp fuse) via a fused connection unit. We recommend that the supply incorporates a switch for ease of operation.
12. Make connections to the electrical supply in accordance with the following code: Live - Brown or Red Neutral - Blue or Black Earth - Green and Yellow
13. This product must be connected to Earth.
14. When making connections, ensure that the terminals are tightened securely and that no strands of wire protrude. Check that the terminals are tightened onto the bared conductors and not onto any insulation. Wrap loose terminal blocks well with insulating tape.
15. Disconnect the fitting from the electrical supply before flash or high voltage testing.
16. If the location of your new fitting requires the provision of a new electrical supply, the supply must conform with the requirements of the Building Regulations making reference to the current edition of the IEE Wiring Regulations (BS7671).
17. You are advised at every stage of your installation to double-check any electrical connections you have made. After you have completed your installation there are electrical tests that should be carried out: these tests are specified in the Wiring Regulations (BS7671) referred to in the Building Regulations. If in doubt, consult a qualified electrician.