

FL-S-KM SERIES INSTALLATION INSTRUCTIONS

Materials Required by Contractor:

- 90°C rated supply conductors
- Sealing Compound

Box Contains:

- FL-S Fixture
- 1 Knuckle Mount

Before Starting Work:

- Ensure that all electrical connections are not live! Take all steps necessary to make sure that electrical connections will not become live accidentally during installation.
- Installation is to be completed by a qualified electrician only.
- Ensure input voltage is correct per label on luminaire



Installation Steps – 1/2" Knuckle Mount:

1. Ensure conduit locknut is screwed onto 1/2" threaded knuckle mount
2. Mount luminaire to any metal 1/2" NPS threaded mounting
3. Route electrical leads through the threaded mounting hole.
Make all electrical connections. Use 90°C rated supply conductors.
4. Adjust angle of the luminaire by loosening the pivot screw. Once desired angle is set, tighten pivot screw.
5. Confirm the lock nut and knuckle mount are both locked in place.
6. Apply sealant to connection point where the knuckle mount is secured to ensure water cannot enter the luminaire or the mounting point.

Black = Live
White = Neutral
Green = Ground

Note: The FL-S Series is intended for outdoor use and is ETL Wet Location Listed.

Caution:

THIS PRODUCT MUST BE INSTALLED IN ACCORDANCE WITH THE APPLICABLE INSTALLATION CODE BY A PERSON FAMILIAR WITH THE CONSTRUCTION AND OPERATION OF THE PRODUCT AND THE HAZARDS INVOLVED

CE PRODUIT DOIT ÊTRE INSTALLÉ SELON LE CODE D'INSTALLATION PERTINENT, PAR UNE PERSONNE QUI CONNAÎT BIEN LE PRODUIT ET SON FONCTIONNEMENT AINSI QUE LES RISQUES INHÉRENTS