

LEAK'STEREO 130'
INTEGRATED AMPLIFIER

INSTALLATION - OPERATION - MAINTENANCE

Specifications

Measurement made with 230V power supply

Model	STEREO 130
D/A Converter	ESS Sabre32 Reference ES9018K2M
Input Sampling Rates	Optical, Coaxial: 44.1kHz~192kHz; USB: 44.1kHz~384kHz (PCM)/DSD64, DSD128, DSD256
Rated Output Power	2 x 45W (8ohm)/2x65W (4ohm)
Total Harmonic Distortion	< 0.005% (30W, 8ohm)
Frequency Response	20Hz~20kHz (+/-0.5dB)
Input Sensitivity	480mV (RCA AUX IN); 4.1mV (phono MM)
Input Impedance	10Kohm (AUX) ; 47Kohm //100pF (phono MM)
Signal to Noise Ratio (S/N)	≥ 108dB (A-weighted, ref.45W)
Pre Output Level	2.3V (Max)
Pre Output Total Harmonic Distortion (THD)	< 0.003%
Pre Output Signal to Noise (S/N)	> 110dB (A-weighted)
Bluetooth Version	4.2
Profile	A2DP
Codec	aptX (priority), SBC
USB Input	1 x USB (B-type)
Digital Audio Inputs	2 x Optical TOSlink , 1 x RCA COAX
Digital Audio Outputs	1 x Optical TOSlink , 1 x RCA COAX
Analog Inputs	2 x RCA (AUX1 , AUX2) , 1 x RCA (phono MM)
Analog Output	1 x RCA (PRE OUT)
Power Requirement (Depends on your area)	220-240V ~ 50/60Hz 100-120V ~ 50/60Hz
Dimensions W x H x D (mm)	302 x 118 x 270 (Metal) 326 x 146 x 276 (Wood)
Carton Size W x H x D (mm)	475 x 248 x 450
Net Weight	7.02kg (Silver) 8.30kg (Walnut)
Gross Weight	9.30kg (Silver) 10.60kg (Walnut)
Finish	Silver/Walnut



Correct disposal of this product. This marking indicates that this product should not be disposed with other household wastes throughout the EU. To prevent possible harm to the environment or human health from uncontrolled waste disposal, recycle it responsibly to promote the sustainable reuse of material resources. To return your used device, please use the return and collection systems or contact the retailer where the product was purchased. They can take this product for environmental safe recycling.