



CR2 2 Pole—Double Throw Control Relay

NR-CR2

NR-CR2/6—STRIP OF 6 WITH COMMON POWER RAILS

CONTROL RELAY

Features:

- 12 or 24 Volt D.C. operation.
- 2 Pole change over contacts.
- 2 Amp. rated relay.
- Low 1.2 mA input current.
- In-built –TR pull-up resistor.
- LED indicates operation.
- Double sided tape mounting.
- Can jumper +VE or –VE to common contacts (C1 & C2).

Applications:

- Dialler interface.
- Electric Door Strike.
- SIU interface.
- Strobe lamp driver.
- Voltage level shifting.

Specifications: (all voltages D.C.)

Operating voltage = 10 - 18V (V Link ON)
 21 - 28V (V Link OFF).

Maximum switch current = 2A at 30V

Life expectancy = 100,000 operations at full load.
 +TR trigger = 2 to +V, 1.2 mA @ 12V, 2.4mA @ 24V.
 –TR trigger = 0 to (+V - 2V), -1.2 mA @ 12V, -2.4mA @ 24V.

Dimensions: (Width x Depth x Height)
 Single Unit - 50mm x 31mm x 15mm
 Strip of 6 - 50mm x 186mm x 15mm



NIDAC Security

2 Cromwell Street
 BURWOOD VICTORIA
 AUSTRALIA 3125

Phone: +61 3 9808 6244
 Fax: +61 3 9808 9335
 E-mail: sales@nidac.com
 Web: www.nidac.com