

AlarmSense

Base



Product overview

Product	AlarmSense Base
Part No.	45681-244

Product information



Caution: System compatibility

AlarmSense bases can only be used in a system that is powered and controlled by purpose designed AlarmSense fire control panels*.



Caution: Series 65 Detectors

Do not use Series 65 detectors on AlarmSense systems. Although they might appear to work initially, their use could cause severe system malfunction. If used with the sounder or sounder visual indicator base the non-priority function will not operate correctly.

AlarmSense bases are fitted with electronic circuitry to monitor the presence of detectors and enable a fault to be signalled if a detector is removed without authorisation. This is also the case with sounder and sounder visual indicator bases.

The AlarmSense Base can be used with the MiniDisc Remote Indicator - Part No. 53832-070.

Technical data

All data is supplied subject to change without notice. Specifications are typical at 24 V, 25°C and 50% RH unless otherwise stated.

Supply wiring	Two wire supply, polarity insensitive
Operating voltage	9 V - 33 V
Quiescent current	< 3 μ A
Head removal load	47 Ω for 10 ms every 4 seconds
Operating temperature	-40 °C to + 80 °C
Humidity (no condensation or icing)	0% to 95% RH
Dimensions	100 mm diameter
Weight	55 g
Materials	Housing: White flame-retardant polycarbonate Terminals: Nickel plated stainless steel

* For further information on suitable fire control panels please contact Apollo Technical Sales: techsales@apollo-fire.com

36 Brookside Road, Havant | Tel: +44 (0)23 9249 2412 | Email: sales@apollo-fire.com
Hampshire, PO9 1JR, UK. | Fax: +44 (0)23 9249 2754 | Web: www.apollo-fire.co.uk

All information in this document is given in good faith but Apollo Fire Detectors Ltd cannot be held responsible for any omissions or errors. The company reserves the right to change the specifications of products at any time and without prior notice.

Comsec Protection Systems

This page has intentionally been left blank