

# ACCESSORIES & COMPONENTS

## 120V Track System

# WAC LIGHTING

Responsible Lighting®



Fixture Type:

Catalog Number:

Project:

Location:

| Accessories                       | Model   | Finish   | Description  |
|-----------------------------------|---|--|--|
| Suspension Loop                   | <b>H-LOOP</b> H Track<br><b>L-LOOP</b> L Track<br><b>J-LOOP</b> J/J2Track | <b>BK</b><br><b>BN*</b><br><b>WT</b><br><b>DB**</b>  | 1 3/8" x 1 3/8" x 3"<br>3 inch electrical loop accepts chain hung fixtures up to 35lbs. Contains compartment for electrical connections.                                     |
| 15' Cord, Male Plug               | <b>HCORD</b> H Track<br>J/J2Track   | <b>BK</b><br><b>WT</b>   | 15'<br>Maximum capacity: 7A, 800W, 120V.   |
| w/ Switch                         | <b>LCORDSET</b> L Track   |  |  |
| T-Bar Drop Ceiling Attachment     | <b>T-BARCLIP</b>  | 1 1/2" x 1 1/4"  | Attaches track to T-bar drop ceilings. Use two for 2 foot or 4 foot tracks, three for 6 foot or 8 foot tracks.   |
| Monopoint Canopy Adapter          | <b>HMP</b> H Track<br><b>LMP</b> L Track<br><b>JMP</b> J/J2Track          | Ø 4 3/4"<br>Ø 4 3/8"<br>5 3/8" x 5 3/8"  | Mount a single H, L or J system track fixture to a junction box. When used with a low voltage track head the transformer box will protrude off of the face of the monopoint. |
| Canopy Plate                      | <b>CP</b>   | 4 1/2" x 4 1/2"  | Covers a standard 4 inch junction box. Use with any powerable connectors.  |
| All Track Suspension Kit          | <b>SK</b>   | <b>18</b> 18"<br><b>24</b> 24"<br><b>36</b> 36"<br><b>48</b> 48"                                 | Extends track from ceiling. Includes track bracket, rod and ceiling canopy.  |
| Suspension Kit Extender           | <b>R</b>  | <b>18</b> 18"<br><b>24</b> 24"<br><b>36</b> 36"<br><b>48</b> 48"<br><b>72</b> 72"                | Use with Rod Coupler (RI) to further extend track from ceiling.  |
| Sloped Ceiling Adapter            | <b>SK14</b>   | <b>BK</b><br><b>BN*</b><br><b>WT</b><br><b>DB**</b>  | Use with suspension kits for sloped ceilings   |
| Rod Coupler                       | <b>RI</b>   |  | Join two rods for suspensions longer than 48".   |
| Suspension Adjustment Collar kit  | <b>SK05</b>   |  | Used when suspension rod is field cut to custom lengths. One kit of two required for each rod. Includes two collars  |
| Low Voltage Track Head Extension  | <b>X</b>  | <b>6</b> 6"<br><b>12</b> 12"<br><b>18</b> 18"<br><b>24</b> 24"<br><b>36</b> 36"<br><b>48</b> 48" | Extends low voltage track heads from track. Specify extension, fixture and finish. Only available as complete unit.  |
| Line Voltage Track Head Extension | <b>H</b>  | <b>18</b> 18"<br><b>24</b> 24"<br><b>36</b> 36"<br><b>48</b> 48"                                 | Extends H Track System line voltage track heads.   |
| Wall Mount Suspension Bracket     | <b>TBKT</b>   | 18"  | Extends track 24" from wall. Use two per 4' length, three per 8' length.   |

\*BN finish only available for H, L, J Track \*\*DB finish only available for H Track

**WAC Lighting**  
www.waclighting.com  
Phone (800) 526.2588 • Fax (800) 526.2585

**Headquarters/Eastern Distribution Center**  
44 Harbor Park Drive • Port Washington, NY 11050  
Phone (516) 515.5000 • Fax (516) 515.5050

**Western Distribution Center**  
1750 Archibald Avenue • Ontario, CA 91760  
Phone (800) 526.2588 • Fax (800) 526.2585