


1. Dismount the ceiling plate by removing the screws that hold the cover of the ceiling plate to its base. Fix the base of the ceiling plate to the ceiling with the screws and plugs supplied, assuring that the electrical cable goes through the hole in the base.
2. Regulate and fix the height of the lighting fixture with the steel cable and its fixation system.
3. Joint the steel cable to the lighting fixture and position the cable. If it is necessary to adjust the height of the lighting fixture, cut the textile cable at the desired height, cut the textile cover very carefully and peel the electrical cable at the recommended measure. Place the transparent thermoretractable protection cover supplied, fixing it with heat from a hair dryer or similar. Pass the cable through the fixation piece and the cable gland, and screw until the cable is fixed.
4. Pass the cable of the lighting fixture through the cover of the ceiling plate and make the connection as indicated in the drawing.
5. Take out the inferior diffuser by unscrewing the piece that holds it to the lighting fixture.
6. Place the lamps and place the diffuser back.

Consumer information:

- Lamps without the IP mark are classed as IP20 and are designed for general interior use, except wet areas (bathrooms, etc.)
- Lamps with the IP mark are designed for exterior use and in wet areas. (E.g. IP54)
- They offer guaranteed protection to people and animals against electrical discharge:
 - Class I: through single electrical insulation and an earthing conductor once correctly connected.
 - ◻ • Class II: through double electrical insulation.
 - ◊ • Class III: these kinds of lamps should be connected at very low voltage levels (generally 12V); therefore there is no risk.
- ▽ • Lamps with this symbol, or without any symbols, can be mounted directly onto normally inflammable surfaces.
- ⚡ • Lamps with this symbol cannot be mounted directly onto normally inflammable surfaces.
 - The safety of this lamp is guaranteed by using a maximum wattage bulb that does not exceed the figure displayed visibly on the lamp.
- ♻️ • The product cannot be treated like conventional domestic waste; it must be taken to the corresponding recycling point for electrical and electronic equipment.

Assembly instructions



B.LUX S.A.

Pol. Ind. Okamika, pab. 1
48289 Gizaburuaga (Bizkaia) Spain
T. (+34) 94 682 72 72
F. (+34) 94 682 49 02
info@grupoblux.com
www.grupoblux.com