

# INSTALLATION INSTRUCTION FOR 4172

**WARNING! SHUT POWER OFF AT FUSE OR CIRCUIT BREAKER .**  
**AVERTISSEMENT! COUPER LE COURANT AU NIVEAU DES FUSIBLES OU DU DISJONCTEUR.**

## PREPARATION

1. Carefully remove the fixture from the carton and check that all parts are included as shown in the illustration.
2. Shut off the power at the circuit breaker and remove old fixture, including the mounting hardware.

## ASSEMBLING THE FIXTURE

3. Thread nut (G) onto all thread (H). Slide cap (F) onto all thread (H) and screw into saddle (E) and tighten with nut (G).
4. Slide the tube (I), cap (J), metal washer (K), plastic washer (L), glass (M), plastic washer (N) and metal washer (O) over all thread (H) and secure with nut (P).
5. Slide the cap (Q) and cap (R) over all thread (H) and secure with cap (S).

## MOUNTING THE FIXTURE (Fig.1)

6. Secure circular strap (B) to junction box using junction box screws (A) (Size:#8-32\*0.6"L). The side of the mounting bar marked "GND" must face out.

## CONNECTING THE WIRES (Fig. 2)

7. Connect the electrical wires as shown in Fig. 2, making sure that all wire connectors are secured. If your junction box has a ground wire (green or bare copper), connect the fixture's ground wire directly to the circular strap (B) using the green screw provided. After the wires are connected, tuck them carefully inside the junction box.

## COMPLETING THE INSTALLATION

8. Raise the fixture (D) over the circular strap (B) and secure with mounting screws (C).
9. Install (2) two medium base bulbs up to 60 watts each or CFL or LED equivalent (not included) in accordance with the fixture specification.

**DO NOT EXCEED THE SPECIFIED WATTAGE!**  
**(NE PAS DEPASSER LA PUISSANCE NOMINALE MAXIMALE!)**

Return the power to the junction box and test the fixture. Your installation is now complete.

