

MONORAIL REMODEL RECESSED TRANSFORMER TECH LIGHTING® LOW-PROFILE-300W ELECTRONIC

PRODUCT FEATURES



LAMPING

It can power lamps totaling up to 300 watts. The transformer installs in similar fashion as a remodel recessed downlight and is concealed inside a housing that recesses above the ceiling. The decorative housing is the only visible portion of the transformer once installed. Should a short occur a fast acting secondary circuit breaker that will safely turn the system off. Once the short has been removed the unit can be reset by simply flipping the wall switch off and back on. Dimmable with a 600 watt low-voltage electronic dimmer. Not compatible with Power Extenders or Standoff Vault Adapter.

MonoRail Remodel Recessed Transformer Low-Profile-300W
Electronic



MonoRail Remodel
Recessed
Transformer Low-
Profile-300W
Electronic

ORDERING INFORMATION

700MOSRR301E FINISH

S SATIN NICKEL

700MOSRR301E _____

JOB NAME _____

NOTES _____




MONORAIL REMODEL RECESSED TRANSFORMER TECH LIGHTING

LOW-PROFILE-300W ELECTRONIC

SPECIFICATIONS

HARDWARE MATERIAL	
SHADE MATERIAL	
NET WEIGHT	1.08 lbs
HEIGHT	2.4in
WIDTH	5in
LENGTH	5in
WET LISTED	
DAMP LISTED	
DRY LISTED	
GENERAL LISTING	ETL Listed
INCLUDES	



LAMPING SPECIFICATIONS

	LED LAMP	INTEGRATED LED	NON LED	NO LAMP
DELIVERED LUMENS				
WATTS				
MAX WATTAGE PER BULB			300W	
INPUT VOLTAGE			120V	
DIMMING TYPE*				
CCT				
CRI				
LED LIFETIME				
L70				
AVERAGE BULB HOURS				
FIELD SERVICEABLE LED				
LAMP BASE				
LAMP SHAPE				
LAMP INCLUDED?			Y	
WARRANTY**			1 Year	

* Dimming information available at www.techlighting.com/Downloads#dimming

** Visit techlighting.com for specific warranty limitations and details.

T20 / T24 INFORMATION

	Integrated LED	Replacement LED Lamp	No Lamp *
This product can be used to comply with California Building Energy Efficiency Standards 2016 Title 24 Part 6.			N/A
This product can be used to comply with California Appliance Efficiency Standards 2016 Title 20 and may be shipped to and sold in California.			N/A

* If a light fixture or component does not include a lamp or light source, it is the responsibility of the customer to select a lamp that meets the T24 and T20 requirements.

