

**RUBICON**  
LIGHTING

**TALLIS 10W - 40W**





**Features:**

- Battery Discharge Up To 2A
- 100% Emergency Light Output
- Remote Box Supplied
- Increased Duration Available On Request
- Provides Emergency Power For Any 230V AC Lamps From 10W - 40W

<b>Power Supply:</b>	220-240V AC   50 - 60Hz
<b>Emergency Duration:</b>	45 Minutes 100% Output
<b>Battery Type:</b>	Nickel Cadmium Or Lead-Acid (LA)
<b>Ingress Protection:</b>	IP20

*\*For detailed luminaire compatibility, please contact your Rubicon Lighting representative.*

Product Code	Battery	Voltage	Dimensions	Remote Box Dimensions
TallisES/10W/NC	Nickel-Cadmium (6X2Ahr)	7.2V	170mm x 45mm x 35mm	220mm x 82mm x 50mm
TallisES/25W/NC	Nickel-Cadmium (10X2Ahr)	12V	250mm x 45mm x 35mm	320mm x 130mm x 50mm
TallisES/25W/LA	Lead-Acid (4.5Ahr)	12V	250mm x 45mm x 35mm	320mm x 130mm x 50mm
TallisES/40W/NC	Nickel-Cadmium (10X2Ahr)	12V	250mm x 78mm x 40mm	320mm x 130mm x 50mm
TallisES/40W/LA	Lead-Acid (4.5Ahr)	12V	250mm x 78mm x 40mm	320mm x 130mm x 50mm



\*E & O.E (Errors And Omissions Excepted)

\*Subject to change without prior notice.

# Contact

## Cape Town

1B Hansen Close,  
Richmond Park,  
Cape Town  
T. +27 21 555 0570

## Durban

Unit L, Nandi Park,  
34 Brickworks Way  
Briardene  
T. +27 31 001 2964

## Namibia – Windhoek

Unit 2, Tesoro Building,  
31 TV More Street  
Windhoek  
T. +264 61 40 0339

## Johannesburg

17 Galaxy Road,  
Unit 5A Galaxy Park,  
Linbro Park  
T. +27 11 262 5179

## Port Elizabeth

216 Main Road,  
Walmer  
Port Elizabeth  
T. +27 41 451 4359