

Preselector Filters Low Band, Aviation, and VHF Preselectors FP20401 Series

FP20401T-3-2.5 Preselector, 2.5 MHz, compact, surface mount, 160-174 MHz

- · Suitable for most standard multicoupling requirements
- · Can be mounted directly on 1.75 " high receiver multicoupler tray
- · Covers the 160-174 MHz frequency range

The 'FP' series preselector filters are compact units that are suitable for most standard receiver multicoupling requirements. Their size permits them to be mounted directly on the 1-3/4 in (44.5 mm) high receiver multicoupler trays.



Region	United States	Europe, Middle East and Africa	Caribbean and Latin America	Canada and rest of the world
Telephone	USA: 1 800 263 3275	International: +44 (0) 1487 84 28 19	International: +1 905 726 7676	Canada: 1 800 263 3275 International: +1 905 727 0165
E-mail	salesusa@sinctech.com	salesuk@sinctech.com	salesla@sinctech.com	salescan@sinctech.com
Product Specificatio	n Sheet	FP20401T-3-2.5	Issue: 1	Dated: 23-10-15




## **Preselector Filters** Low Band, Aviation, and VHF Preselectors FP20401 Series

A Norsat Company Norsat

MHz	160 to 174	
	1.5:1	
W	20	
	TNC-Female	
	TNC-Female	
MHz	2.5	
dB	1.5	
	W	1.5:1 W 20 TNC-Female TNC-Female MHz 2.5

Mechanical Specifications		
Width	in (mm)	4.2 (107)
Depth	in (mm)	4.9 (124)
Length/ Height	in (mm)	1.3 (33)
Weight	lbs (kg)	1.1 (0.5)
Actual Shipping weight	lbs (kg)	2 (0.91)
Shipping dimensions	in (mm)	13x9x3 (330x229x76)

Environmental Specifications			
Temperature range	°F (°C)	-22 to +140 (-30 to +60)	



Region	United States	Europe, Middle East and Africa	Caribbean and Latin America	Canada and rest of the world
Telephone	USA: 1 800 263 3275	International: +44 (0) 1487 84 28 19	International: +1 905 726 7676	Canada: 1 800 263 3275 International: +1 905 727 0165
E-mail	salesusa@sinctech.com	salesuk@sinctech.com	salesla@sinctech.com	salescan@sinctech.com
Product Specification	n Sheet	FP20401T-3-2 5	Issue: 1	Dated: 23-10-15