

A Norsat Company in Norsat

FP40137 High Q, 3/4 Wave Bandpass Cavity, Single 7" Cavity, 806-960 MHz

- · Aluminum cylinder with brass and copper coaxial inner conductor
- · Silver plating and chromate conversion coating, limit corrosion and enhance performance
- · Temperature compensated for extremely low frequency drift

Sinclair's FP series cavity filters are the building blocks of the finest antenna systems. These filters pass a band of frequencies while attenuating frequencies on either side of the desired frequency band. The insertion loss of the passband may be preset at the factory or adjusted in the field. The amount of attenuation (selectivity) can be increased by increasing the insertion loss or using multiple cavities in series. Filter design must recognize the extremely close tolerances required to assure flawless performance over temperature when small variations in electrical wavelength mean significant changes in frequency response curves.

The FP series band pass filters are designed to:

- •Protect one receiver further from front-end overload by carriers of co-located transmitters.
- •Suppress IM generation in one transmitter by protecting it further from incoming carriers of co-located transmitters (usually in conjunction with a ferrite isolator).
- •Suppress sideband noise of a single transmitter on co-located receiver frequencies.
- •Generally, "Protect One from Many."



Region	United States	Europe, Middle East and Africa	Caribbean and Latin America	Canada and rest of the world
Telephone	USA: 1 800 263 3275	International: +44 (0) 1487 84 28 19	International: +1 905 726 7676	Canada: 1 800 263 3275 International: +1 905 727 0165
E-mail	salesusa@sinctech.com	salesuk@sinctech.com	salesla@sinctech.com	salescan@sinctech.com

Sinclair's commitment to product leadership may result in improvement or change to this product

Copyright © Sinclair Technologies

Dated: 08-10-13



Cavity Filters 700-1000 MHz Bandpass Cavities FP40137 Series

Notes *1 : at 0.75 dB I.L.

A Norsat Company in Norsat

Frequency Range	MHz	806 to 960	
Input VSWR (max)		1.5:1	
Impedance	Ω	50	
Number of Cavities		1	
Average Power Input (max)	W	280	*1
Input Connectors		N-Female	
Output Connectors		N-Female	
Insertion loss (min)	dB	0.8	
Mechanical Specifications Depth	in (mm)	7 (178)	
Depth	in (mm)	7 (178) 16.7 (424)	
•	in (mm) in (mm) in (mm)	7 (178) 16.7 (424) 7 (178)	
Depth Length/ Height	in (mm)	16.7 (424)	
Depth Length/ Height Width	in (mm) in (mm)	16.7 (424) 7 (178)	
Depth Length/ Height Width Weight	in (mm) in (mm)	16.7 (424) 7 (178) 5.5 (2.5)	

Region	United States	Europe, Middle East and Africa	Caribbean and Latin America	Canada and rest of the world
Telephone	USA: 1 800 263 3275	International: +44 (0) 1487 84 28 19	International: +1 905 726 7676	Canada: 1 800 263 3275 International: +1 905 727 0165
E-mail	salesusa@sinctech.com	salesuk@sinctech.com	salesla@sinctech.com	salescan@sinctech.com
Droduct Specification	n Chaot	ED/0137	legue: 16	Dated: 08 10 13