

FP40615CLB-1 Combine preselector, 15 MHz bandwidth, 806-821 MHz

- Covers the entire 806-821 MHz band
- 1 dB insertion loss over the passband
- 50 dB attenuation 23 MHz away from center frequency



www.sinctech.com

Region	United States	Europe, Middle East and Africa	Caribbean and Latin America	Canada and rest of the world
Telephone	USA: 1 800 263 3275	International: +44 (0) 1487 84 28 19	International: +1 905 726 7676	Canada: 1 800 263 3275 International: +1 905 727 0165
E-mail	salesusa@sinctech.com	salesuk@sinctech.com	salesla@sinctech.com	salescan@sinctech.com
Product Specification Sheet EPR 016141		FP40615CLB-1	Issue: 5	Dated: 27-08-15 Dated: 15-09-04

Electrical Specifications

Frequency Range	MHz	806 to 821
Pass band Insertion Loss (max)	dB	1
Input VSWR (max)		1.5:1
Selectivity Bandwidth @ 50 dB	MHz	46
Impedance	Ω	50
Average Power Input (max)	W	50
Input Connectors		BNC-Female
Output Connectors		BNC-Female
Bandwidth at specified insertion loss	MHz	15

Notes

*1 : To mount onto tray

Mechanical Specifications

Width	in (mm)	8.6 (218)
Depth	in (mm)	4.75 (121)
Length/ Height	in (mm)	1.5 (38)
Mounting configurations		Mounting holes provided *1

Environmental Specifications

Temperature range	°F (°C)	-22 to +140 (-30 to +60)
-------------------	---------	--------------------------

Region	United States	Europe, Middle East and Africa	Caribbean and Latin America	Canada and rest of the world
Telephone	USA: 1 800 263 3275	International: +44 (0) 1487 84 28 19	International: +1 905 726 7676	Canada: 1 800 263 3275 International: +1 905 727 0165
E-mail	salesusa@sinctech.com	salesuk@sinctech.com	salesla@sinctech.com	salescan@sinctech.com