

Transmitter Combiners UHF and Tetra Transmitter Combiners TJ3x1y-R-z Series

### TJ3113-R-3 Cavity-Ferrite Transmitter Combiner, 3 Channels, 7" Cavities, 406-440 MHz

- · Low loss broad band single stage isolators
- Allows for minimum Tx-Tx spacings of 200 KHz
- Expandable for more channels
- · Uses high 'Q' 1/4 wave bandpass cavity filters

Sinclair's 'TJ3x1y-R-z' series cavity ferrite transmitter combiners are available in 2 to 5 channel configurations for use in systems from 406-512 MHz. Each channel on these combiners includes a low-loss, broad band single or dual-stage isolator and High 'Q' 1/4 wave bandpass cavity filter suitable for close channel separations, typically 200 KHz.

The 'TJ3x1y-R-z' series combiners can be expanded to 20 channels. For expansion please contact the Sinclair Systems group.


The naming convention and options for the TJ3-R are as follows:

TJ3x1y-R-z

Isolator typex=1Single stagex=2Dual stage

y= number of channels

Sub-band z=3 406-440 MHz z=4 430-470 MHz z=5 459-512 MHz



Region	United States	Europe, Middle East and Africa	Caribbean and Latin America	Canada and rest of the world	
Telephone	USA: 1 800 263 3275	International: +44 (0) 1487 84 28 19	International: +1 905 726 7676	Canada: 1 800 263 3275 International: +1 905 727 0165	
E-mail	salesusa@sinctech.com	salesuk@sinctech.com	salesla@sinctech.com	salescan@sinctech.com	
Product Specification Sheet EPR 018652		TJ3113-R-3	Issue: 1	Dated: 22-08-19 Dated: 24-11-11	
Customer Tech Manual 006289		Sinclair's commitment to product leadership may result in improvement or change to this product			

It's commitment to product leadership may result in improvement or change to this pro-Copyright © Sinclair Technologies

www.sinctech.com



## A Norsat Company 🔟 Norsat

# Transmitter Combiners UHF and Tetra Transmitter Combiners TJ3x1y-R-z Series

Electrical Specifications			
Frequency Range	MHz	406 to 440	
Number of channels		3	
Input Connectors		N-Female	
Output Connectors		N-Female	
Input VSWR (max)		1.25:1	
Output VSWR		2:1	
Insertion Loss (typ) Tx to Ant	dB	3.2	*1
Maximum Input Power (per channel)	W	125	
Frequency separation (min)	MHz	0.2	
Isolation Tx to Tx	dB	35	
Isolation antenna to Tx	dB	25	
Cavity electrical length		1/4	
Cavity electrical length		1/4	

Notes

**Ordering Information** 

Specify one Tx frequency per channel at time of order.


#### **Mechanical Specifications**

Width	in (mm)	19 (483)	
Depth	in (mm)	14.8 (376)	
Length/ Height	in (mm)	15.3 (389)	
Weight	lbs (kg)	30 (13.62)	
Actual shipping weight	lbs (kg)	40 (18.16)	
Shipping dimensions	in (mm)	20x16x21 (508x406x533)	

°F (°C)

### **Environmental Specifications**

Temperature	range



Region	United States	Europe, Middle East and Africa	Caribbean and Latin America	Canada and rest of the world
Telephone	USA: 1 800 263 3275	International: +44 (0) 1487 84 28 19	International: +1 905 726 7676	Canada: 1 800 263 3275 International: +1 905 727 0165
E-mail	salesusa@sinctech.com	salesuk@sinctech.com	salesla@sinctech.com	salescan@sinctech.com
Product Specification Sheet EPR 018652 Customer Tech Manual 006289		TJ3113-R-3	Issue: 1	Dated: 22-08-19 Dated: 24-11-11
		Sinclair's commitment to product leadership may result in improvement or change to this product		

-22 to +140 (-30 to +60)

Copyright © Sinclair Technologies

<sup>\*1 : @ 250</sup> kHz Tx-Tx spacing