

Cards	Stack	Add(hex)	Add
Smart FAN	0	3	3
	1	4	4
I/O Learning HAT	0	5	5
Sixteen Digital Inputs v >= 3.0	0	0d	13
	1	0c	12
	2	0b	11
	3	0a	10
	4	9	9
	5	8	8
	6	7	7
	7	6	6
Four Relays four HV Inputs v >= 4.0	0	0e	14
	1	0f	15
	2	10	16
	3	11	17
	4	12	18
	5	13	19
	6	14	20
	7	15	21
Eight Relays	0	27	39
	1	26	38
	2	25	37
	3	24	36
	4	23	35
	5	22	34
	6	21	33
	7	20	32
Home Automation	0	28	40
	1	29	41
	2	2A	42
	3	2B	43
	4	2C	44
	5	2D	45
	6	2E	46
	7	2F	47
Smart FAN V4	0	2D	45
	1	2C	44
Super Watchdog	0	30	48

Megaio (obsolete)	0	31	49
	1	32	50
	2	33	51
	3	34	52

Eight Relays	0	3F	63
	1	3E	62
	2	3D	61
	3	3C	60
	4	3B	59
	5	3A	58
	6	39	57
	7	38	56

Four Relays four HV Inputs v < 4.0	0	3F	63
	1	3E	62
	2	3D	61
	3	3C	60
	4	3B	59
	5	3A	58
	6	39	57
	7	38	56

Megaio Industrial (obsolete)	0	38	56
	1	39	57
	2	3A	58
	3	3B	59

RTD Data Acquisition	0	40	64
	1	41	65
	2	42	66
	3	43	67
	4	44	68
	5	45	69
	6	46	70
	7	47	71

Building Automation	0	48	72
	1	49	73
	2	4A	74
	3	4B	75
	4	4C	76
	5	4D	77
	6	4E	78
	7	4F	79

Industrial Automation	0	50	80
	1	51	81
	2	52	82
	3	53	83
	4	54	84
	5	55	85
	6	56	86
	7	57	87

Sixteen Digital Inputs v<3.0	0	27	39
	1	26	38
	2	25	37
	3	24	36
	4	23	35
	5	22	34
	6	21	33
	7	20	32

IND SERIES (under development)	0	58	88
	1	59	89
	2	5A	90
	3	5B	91
	4	5C	92
	5	5D	93
	6	5E	94
	7	5F	95

Three 40A/240V Relays	0	60	96
	1	61	97
	2	62	98
	3	63	99
	4	64	100
	5	65	101
	6	66	102
	7	67	103

Sixteen Relays	0	27	39
	1	26	38
	2	25	37
	3	24	36
	4	23	35
	5	22	34
	6	21	33
	7	20	32