



12V OWL

EVO-OWL-12030-G1

BATTERY SPECS

Chemistry: LFP
Voltage: 12V
Capacity: 3 kWh
Amp Hours: 230 Ah
Operating Voltage Range: 11.2V - 14.6V
Charging Voltage: 14.6V
Max Charging Voltage: 14.8V



WARNING: Do NOT exceed max charging voltage.

Cell Configuration: 4S1P

Charge Temperature Range:
0°C (32°F) / 55°C (131°F)

Discharge Temperature Range:
-20°C (-4°F) / 55°C (131°F)

Optimal Discharge Temp. Range:
15°C (59°F) / 35°C (95°F)

Storage Temperature Range:
-5°C (23°F) / 35°C (95°F) (Max 6 months)

BMS SPECS

Max Peak Discharge: 300A (Over 6 Seconds)

Max Continuous Power: 1920W

Max Continuous Discharge: 150A

Max Charge Current: 150A

BATTERY SIZE

Weight: 47 lbs. (21.3 kg)

Width: 7.2 in (182.9 mm)

Depth: 10.1 in (256.5 mm)

Height: 12 in (304.8 mm)



PARAMETERS

Note: Bulk, Absorption, Float, and Equalize are not applicable to lithium batteries but are included here with the correct numbers to input into your charge controller as they are our most commonly requested parameters.

Charge Voltage: 13.75V

Bulk Voltage: 14.1V (Not Applicable to Lithium Batteries)

Absorption Voltage: 13.75V (Not Applicable to Lithium Batteries)

Absorption Time: 0 Minutes (Not Applicable to Lithium Batteries)

Float Voltage: 13.75V (Not Applicable to Lithium Batteries)

Equalize: Off (Not Applicable to Lithium Batteries)

Low Voltage Cutoff: 10.5V

High Voltage Cutoff: 14V

Suggested Inverter Low Voltage Setting: 11V

FAQ'S

How do I connect this battery into my existing system?

Our product uses a standard 175A Anderson connector. A single battery order will include a 175A connector to Ring Terminal cable for ease of installation.

How many times can I put this battery in parallel / series?

This battery is not series capable but can be connected in parallel up to eight times. Make sure that the total amount of these batteries in your configuration never exceeds eight total batteries. When connecting batteries in parallel, make sure all batteries are within 1 volt of one another.

How long will my battery last, and what do I do at the end of its life?

Lithium-ion batteries can be cycled from 3000 to 5000 times. If you cycle the battery daily then you can get more than 10 years of use from your battery. When your battery is at the end of its lifespan, contact us and we'll recycle it for you, free of charge!

Can I connect into this battery's BMS to get extra info?

Our BMS is just there to keep your battery safe and healthy, it does not have the ability to network with any charge controllers or inverters for extra read-outs.

What is the warranty on this battery?

We offer a comprehensive 10 year warranty on all of our batteries. You can read more about our warranty at batteryevo.com/10-years-warranty/.

Contact Us

Phone: (818) 337-0929

Email: Sales@batteryevo.com

Hours: Monday - Friday 9:00 AM to 5:00 PM PST

Address: 8966 Mason Ave, Chatsworth, CA 91311