

## Power Draw & Noise Level

### Treadmill Base

Power Draw (Amps/Watts)	TR1000	TR1200"	TR5000"	Noise (dBA) TR1000	Noise (dBA) TR1200	Noise (dBA) TR5000
Resting	0.003 / 0.24	0.003 / 0.24	0.003 / 0.24	0	0	0
200 lbs at 2 MPH	2.48 / 187	2.48 / 187	2.45 / 185	51.7	51.7	51.7

### Bike Base

Power Draw (Amps/Watts)	C3-DT
Resting	0.015 / 121
Max	0.031 / 2.48

### Height Adjustable Desks

Power Draw (Amps/Watts)	48"	60"	72"	Noise (dBA)
Resting	0.02 / 0.5 0	.02 / 0.5 0	.02 / 0.5	44.9
No Load	0.96 / 77	1.05 / 89	1.19 / 96	44.9
120 lbs	1.82 / 151	2.01 / 159	2.07 / 177	44.9

Electrical Requirements	
Volts	115V Nominal
Circuit	NEMA 5-15P; non GFCI outlet and breakers
Breaker (Minimal Requirement)	15A
Power Supply Output (Bike base only)	6 Volts, 1 Amp