



Model No:
DS-3201

Quick Installation Guide

Wi-Fi smart plug
(US 3-pin)



Version 1.00
(English | Indonesian)

1 Package Contents



x 1



x 1


Note:

1. The picture illustrations in this document may appear different from actual product.
2. If any of the stated items above are not included in your package, please consult your reseller immediately.

2 Overview



Front view



Side view



Rear view

2 Overview

Interface and Buttons

1. Status LED
2. Power/Reset Button

Status LED:

LED Behavior	Description
Off	Unit is Off
Solid Blue	Unit is On
Fast Blinking	Ready for Auto Add Configuration (setup)
Slow Blinking	Ready for AP Mode Configuration (setup)

Power/Reset Button:

Activity	Action Required
To power On / Off the Smart Plug	Press one time
To reset the Smart Plug to factory default	Press and hold for 6 seconds
To switch between <u>Auto Add</u> and <u>AP Mode</u> configurations	Press and hold for 6 seconds

3 Installation

A. Preparation

1. Place the Smart Plug and your mobile device within three feet of the router

Note:

- Make sure the phone is connected to the router wirelessly.
 - Smart Plug is operating only at 2.4GHz Wireless N standard
2. Download, install and create an account on ProLink mEzee App. Scan below QR code to download from Google Store or Apple App Store. Alternatively, search for "mEzee".



mEzee



QIG

For Google Assistant / Amazon Alexa users:

Step 1. Complete the steps in this Quick Installation Guide


Step 2. Follow the setup instruction available from

<https://prolink2u.com/smart-home/smart-plug/ds-3201-us/download/>

3 Installation

B. Setting up Smart Plug


1. Tap on Add Device or + from the main screen
2. Proceed with **Method A: Auto Add Configuration** or **Method B: AP Mode Configuration**



3 Installation


Method A: Auto Add Configuration (Ensure the mobile phone's Bluetooth is enabled)

1. Click **Go to add**



3 Installation

2. Select 2.4GHz Wi-Fi Network and enter password



3 Installation


- Once connected, proceed to name this device for easy reference and tap **Done**



3 Installation

Method B: AP Mode Configuration (Ensure the mobile phone's Bluetooth is disabled)

1. Select **Smart Plug** and tap **Socket(Wi-Fi)**
2. Select 2.4GHz Wi-Fi Network and enter password




3 Installation

3. Toggle the top right-hand option to **AP Mode** if it shows otherwise
4. Ensure the LED indicator is blinking slowly, otherwise hold the reset button for about 6 seconds




3 Installation

5. Tick **Confirm the indicator is blinking slowly** > tap **Next**
6. Tap **Go to Connect** and connect your mobile phone with **Prolink-XXXX** or **PROLiNK-XXXX** or **SmartLife-XXXX** SSID. Then return back to the App



3 Installation

7. Once connected, proceed to name this device for easy reference and tap **Done**



1 Isi Kemasan



x 1



x 1


Catatan:

1. Gambar ilustrasi dalam dokumen ini mungkin tampak berbeda dari produk yang sebenarnya
2. Jika salah satu item yang disebutkan di atas tidak termasuk dalam paket Anda, silakan segera berkonsultasi dengan reseller Anda

2 Keterangan Gambar



Tampak hadapan



Tampak sisi



Tampak belakang

2 Keterangan Gambar

Antaramuka dan Tombol

1. Status LED
2. Power/Reset Button

Status LED:

Perilaku LED	Deskripsi
Off	Unit tidak aktif
Biru Solid	Unit aktif
Berkedip Cepat	Siap untuk pengaturan lewat Auto Add Configuration (Setup)
Berkedip Lambat	Siap untuk pengaturan lewat AP Mode Configuration (Setup)

Power/Reset Button:

Aktivitas	Tindakan yang diperlukan
Untuk menghidupkan/mematikan Smart Plug	Tekan satu kali
Untuk mereset Smart Plug ke default pabrik	Tekan dan tahan selama 6 detik
Untuk beralih di antara <u>Auto Add</u> dan <u>AP Mode</u> Configurations	Tekan dan tahan selama 6 detik

3 Instalasi

A. Persiapan

1. Tempatkan Smart Plug and ponsel sekitar 3 kaki dari router

Catatan:

- Pastikan ponsel terhubung ke router secara wireless
- Smart Plug hanya beroperasi pada Wireless N 2.4GHz

2. Unduh, instal, dan buat akun melalui Prolink Aplikasi mEzee Pindai kode QR di bawah ini ke unduh dari Google Store atau Apple App Store atau, cari "mEzee".



mEzee



QIG

Untuk pengguna Google Assistant / Amazon Alexa:

Langkah 1. Selesaikan langkah-langkah dalam Panduan Pemasangan Cepat ini


Langkah 2. Ikuti instruksi pengaturan yang tersedia dari

<https://prolink2u.com/smart-home/smart-plug/ds-3201-us/download/>

3 Instalasi

B. Pengaturan Smart Plug


1. Ketuk Tambah Perangkat atau + dari layar utama
2. Lanjutkan dengan **Metode A: Konfigurasi Tambah Otomatis** atau **Metode B: Konfigurasi Mode AP**



3 Instalasi


Metode A: Auto Add Configuration
(Pastikan Bluetooth ponsel diaktifkan)

1. Klik **Go to add**




3 Instalasi

3. Pilih Jaringan Wi-Fi 2.4GHz dan masukkan kata sandi



3 Instalasi


4. Setelah terhubung, lanjutkan untuk memberi nama perangkat ini untuk referensi mudah dan ketuk **Done**



3 Instalasi

Metode B: AP Mode Configuration
(Pastikan Bluetooth ponsel dinonaktifkan)

1. Pilih "**Smart Plug**" dan ketuk **Socket (Wi-Fi)**
2. Pilih Jaringan Wi-Fi 2.4GHz dan masukkan kata sandi




3 Instalasi

3. Alihkan opsi kanan atas ke Mode AP jika menunjukkan sebaliknya
4. Pastikan indikator LED berkedip perlahan, jika tidak tahan tombol reset selama sekitar 6 detik




3 Instalasi

5. Centang **Confirm the indicator is blinking slowly** ketuk > Next
6. Ketuk **Go to Connect** dan hubungkan ponsel Anda dengan **ProLink-XXXX** atau **PROLiNK-XXXX** atau **SmartLife-XXXX** SSID. Kemudian kembali ke Aplikasi



3 Instalasi

7. Setelah terhubung, lanjutkan untuk memberi nama perangkat ini dengan mudah referensi dan ketuk Selesai



Worldwide Customer Care Centers

INDONESIA Office

PT PROLINK INTIDATA NUSANTARA

Walk-In : Jl. Cideng Barat No. 79, Jakarta Pusat 10150, Indonesia.

Telephone : +62 21 3483 1777

Email Support : support.id@prolink2u.com

MALAYSIA Office

FIDA SYSTEMS (M) SDN BHD

Walk-In : 29 Jalan USJ 1/31, 47600 Subang Jaya,
Selangor Darul Ehsan, Malaysia.

Telephone : +60 3 8024 9151

Email Support : support.my@prolink2u.com

SINGAPORE Office

FIDA INTERNATIONAL (S) PTE LTD

Walk-In : Block 16 Kallang Place #06-02,
Kallang Basin Industrial Estate, Singapore 339156.

Telephone : +65 6357 0668

Email Support : support@prolink2u.com

Technical Support Hotline

INDONESIA : +62 21 3483 1717

MALAYSIA : +60 3 8023 9151

SINGAPORE : +65 6357 0666

Note: Closed on Saturdays, Sundays and local/regional Public Holidays.

Register online for your Product Warranty at www.prolink2u.com

Prolink is a registered trademark of Fida International (S) Pte Ltd. Other brands and product names are trademarks or registered trademarks of their respective holders. Product images are purely for illustrative purposes and may differ from the actual product. Specifications are subjected to changes without prior notice. Copyright © 2021 Fida International (S) Pte Ltd.