

## LED OUTDOOR

### ROUND GARAGE CANOPY

CCT & WATTAGE SELECTABLE - OPTIONAL UPWARD LIGHT

100W - SENSOR READY




LR40720

30W 50W 75W 100W



OPTIONAL  
10% UPWARD  
LIGHT



FRONT VIEW

SENSOR READY



COLOR SELECTABLE

3000K 4000K 5000K

WATTAGE  
SELECTABLE

4 OPTIONS



OPTIONAL  
10% UPWARD  
LIGHT




SENSOR  
READY

3/4" POLE  
MOUNT  
READY



DIMMABLE  
0-10V

120-  
277V



WET  
LOCATION  
RATED  
IP-65



5  
YEAR  
WARRANTY

## ELECTRICAL

| MODEL | DESCRIPTION                                                             | POWER | LUMEN | INPUT VOLTS | EFFICACY | LIFETIME | COST/YR |
|-------|-------------------------------------------------------------------------|-------|-------|-------------|----------|----------|---------|
| 100W  | LR40720<br>LEDNCN100/3CCT/4WO/UNV/RD/WT<br>[Blank;(PT),(MS),(EM),(EMS)] | 30    | 3600  | 120-277V    | 120      | 50,000   | \$12.04 |
|       |                                                                         | 50    | 6000  |             |          |          |         |
|       |                                                                         | 75    | 9000  |             |          |          |         |
|       |                                                                         | 100   | 12000 |             |          |          |         |

## PHOTOMETRIC

| MODEL   | DESCRIPTION                  | COLOR (CCT)       | TEMP           | FLOOD | CRI | UL LISTED | DLC      |
|---------|------------------------------|-------------------|----------------|-------|-----|-----------|----------|
| LR40720 | LEDNCN100/3CCT/4WO/UNV/RD/WT | 3000K/4000K/5000K | CCT SELECTABLE | 150°  | 80  | YES       | S-LCNZVF |

\*Blank= No Sensor or Emergency Driver function, "MS"= Motion sensor; "PT"= Photocell; "EM"= Emergency driver;  
"EMS"= Emergency Driver & Motion Sensor

## DIMENSIONS

