



Perfect for anywhere you might want to manually turning lights on, but know they'll turn off automatically, such as children's bedrooms. The adorne Manual On/Auto Off Motion Sensor Switch provides combination control by allowing you to manually turn lights on when entering a room, and automatically turn the lights off for you when you leave, thanks to motion-sensing technology. Use this device on its own to control a light or fixture from a single location one location, or combine with additional switches for controlling a single light source from multiple locations in 3 or 4-way applications. (four-way operation). Made exclusively for use with screwless Wall Plates from the adorne® Collection, sold separately.

Features & Benefits

Installs in 15 minutes or less, fitting into an existing electrical box. No new wiring required for typical installation.

More color options available to fit any style, including finishes to match current hardware and lighting trends.

Complete the look with a stunning, screwless adorne® Wall Plate, not included. Available in a range of contemporary colors and finishes. Coordinate with other designer switches & outlets.

Specifications

General Info

Color	Magnesium	UPC Number	785007023282
Country Of Origin	China	Product Line	Pass & Seymour
Number of Switches	1	Warranty Type	Limited Lifetime Warranty
Standard	cULus		

Technical Information

Wattage	600 W	Number of Poles	Single Pole, 3-Way
Number of Gangs	1	Voltage	120 V
Sensitivity	Major Motion 35' Minor Motion 20'	Mounting Type	Box
Sensing Range	180° 600 sq ft	Connector	Screw Terminals

Load	Incandescent or LED lamp: 0-600 Watt Fluorescent lamp: 0-600 VA Fan Motor: 1/6 hp	Connection Type	Internal Pressure Plates
------	---	-----------------	--------------------------

Environmental Conditions	Residential Indoor Use Only
--------------------------	-----------------------------
