
## **ASSEMBLY INSTRUCTIONS**





Item # CHD 2916

WE RECOMMEND INSTALLATION OF THIS LIGHTING FIXTURE BE DONE BY A LICENSED ELECTRICIAN.

WARNING\*\*\*SWITCH OFF THE MAIN ELECTRICAL SUPPLY FROM THE MAIN FUSE BOX/CIRCUIT BREAKER BEFORE INSTALLATION.

INSPECT ITEM CAREFULLY BEFORE ATTEMPTING TO INSTALL. IF THERE IS ANY DAMAGE OR OBVIOUS DEFECT. DO NOT INSTALL.

ITEM MAY NOT BE RETURNED ONCE IT HAS BEEN INSTALLED.

NOTE: CAREFULLY UNPACK EACH PIECE IN TOP LAYER OF PACKING PRIOR TO REMOVING. RETAIN ALL PACKING MATERIAL UNTIL INSPECTION AND INSTALLATION ARE FINAL.

- 1. Carefully remove all parts from the box.
- 2. Remove the mounting plate (C) from the backplate (F) by loosening the set screws (D) with the set screwdriver (E) provided.
- 3. Install the mounting plate (C) to the junction box and secure with the mounting screws (B).
- 4. Wrap the fixture ground wire to the green ground screw on the mounting plate (C) and secure, then connect to the ground wire in the junction box using the wire nut (A).
  IT IS IMPERATIVE THAT THIS FIXTURE BE GROUNDED.
- 5. Connect the fixture white wire to the neutral wire in the junction box using the wire nut (A).
- Connect the fixture black wire to the hot wire in the junction box using the wire nut (A).
   DO NOT REVERSE THE HOT AND NEUTRAL CONNECTIONS OTHERWISE SAFETY WILL
   BE COMPROMISED.
- 7. Install the backplate (F) to the mounting plate (C) and secure with the set screws (D) with the set screwdriver (E) provided.
- 8. Insert bulb (not included) into the socket.
- Attach the rubber washer (J) to either side of alabaster panel (G) and secure to the bracket (H) with the cap nut (I).
- 10. Hang the bracket (H) to the hook on the fixture.
- 11. Installation is complete, turn on power at fuse or circuit breaker.









<sup>\*\*\*</sup>Clean with a dry, soft cloth only. Use no harsh abrasives or chemical agents.