

**3-CHANNEL WIRELESS PWM RECEIVER**



CODE
BL-PC-LT30535A

FUNCTION
<ul style="list-style-type: none"> <li>- For use with sender BL-PC-DIM-2001</li> <li>- Wireless communication of PWM signal</li> <li>- Unlimited receivers can be used in conjunction with a single sender</li> <li>- Frequency of 2.4GHz ISM 64 channels</li> </ul>

OUTPUT CURRENT	MAX. LOADING	VOLTS
3 × 5A channels (15A)	75W	5V DC
	180W	12V DC
	360W	24V DC

DIMENSIONS	W44 × L175 × H30mm
HOUSING	PVC casing
MOUNTING	2 × mounting tabs
WARRANTY	5 years
COMPLIANCE	

OPERATING TEMP.	-20°C ~ +55°C
INGRESS PROTECTION	Indoor use only
CONNECTION METHOD	Concealed screw terminals
CONTROL	Requires signal from Wireless PWM Dimmer Sender BL-PC-DIM-2001
FREQUENCY	2.4GHz <i>Up to 300 metres. Steel, concrete, or environmental conditions will inhibit transmission.</i>
MAX. DISTANCE FROM POWER SUPPLY	Recommended under 10 metres <i>For specific projects contact Bright Light</i>