



Serious projects demand serious lighting, look no further than the Energizer **HARDCASE PROFESSIONAL®** Rechargeable Spotlight. Constructed with rugged steel and rubber materials, this light is designed to meet the most demanding jobs and withstand drop after drop during use. With high power LEDs, the powerful beam can span the distance of four stadium fields, while high and low mode options allow the user to maximize brightness or runtime. And with a convenient, rechargeable design, users get a great performance time and time again with the ability to charge devices via USB charge out.

Lumens	Runtime	Beam Distance	Drop	Water Ingress
FL1 STANDARD 1000 LUMENS	FL1 STANDARD 7h	FL1 STANDARD 550m	FL1 STANDARD 3m	FL1 STANDARD IPX4



DESIGN BENEFITS	
✓	Shatterproof lens
✓	Exceptionally durable construction for the most demanding jobs
✓	Convenient rechargeable power supply w/ USB charge out to charge devices
✓	High and low modes for optimized brightness and runtime control
✓	Built-in lanyard slot

PERFORMANCE BENEFITS	
✓	LEDs provide a bright spot for a variety of tasks
✓	Powerful beam distance to see objects far away
✓	Water resistant for outdoor tasks
✓	Rechargeable Lithium-Ion power supply

LIGHT AND POWER SOURCE	
✓	Features LED Technology
✓	5000K CCT
✓	60 CRI
✓	Powered by 21700 4800 mAh Lithium-Ion rechargeable battery

BATTERY SPECIFICATIONS	
Battery Type	Energizer Rechargeable Li-Ion
Battery Size	21700 4800 mAh
Number of Cells	1

PRODUCT SPECIFICATIONS	
Weight:	560 Grams/ 19.8 Ounces
Dimensions:	203mm x 89mm x 64mm 8" x 3.5" x 2.5"

BATTERY PERFORMANCE			
Modes	Lumens (lm)	Runtime (h)	Beam Distance (m)
High	1000	7	550
Low	250	28	350

ELECTRICAL CHARACTERISTICS	
Nominal Power Consumption:	13W
Batteries:	1 Energizer Lithium ion 21700 4800mAh 3.7V DC
LED Specifications:	LED 3.0V cc / 3100 mA

Modes
High/Low

CERTIFICATES AND COMPLIANCE	
EMC, EN62471, FCC	

DISCLAIMERS

Tested according to ANSI FL1 Standards.
 This device complies with part 15 of the FCC Rules.
 Operation is subject to the following two conditions: (1) This device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation.



Av. Andrés Avelino Cáceres 320 – Miraflores
ventas@dimerc.pe / dimerc-industrial.pe

Publish Date: 14 Jan 2022



OPERATING INSTRUCTIONS

1. Press on/off button to turn on.
2. Press 1 time for high.
3. Press 2 time for low.
4. Press again for off.

BATTERY CHARGING INSTRUCTIONS

1. Non-removable battery.
2. To charge use included USB cord and plug light into any USB charging port. For best charging performance, do not use light while charging.
3. Charging Indicator light is located near charging port. Charging Indicator light flashes while charging. Charging Indicator light is solid when fully charged.
4. Flashlight can be used to charge a cellphone or other portable device. Use charging cord that came with your device and plug into the large USB port on the front of the light. For best device charging performance, do not use light while charging a device.



Av. Andrés Avelino Cáceres 320 – Miraflores

ventas@dimerc.pe / dimerc-industrial.pe