



## PS-DD1000

Wholesale DC / DC AUTO Converter, Booster/Regulator

### Features:

- ✧ Input voltage: 8~24VDC
- ✧ Output voltage:12VDC
- ✧ Output current: 1A (for IR camera, and long distance transmit )
- ✧ Output short circuit protection
- ✧ Overload protection



### Specifications:

Item	DC/DC AUTO Converter	
Model Number	PS-DD1000	
Ports	SINGLE	
Input Voltage	DC 8V-24V	
Output Voltage	DC 12V	
Output Current	Nominal 1A	
Reset Tim	1 Second	
Input Connector	Screw Terminal	
Output Connector	Screw Terminal	
Operating Conditions	Temperature: -10° C ~ +40° C	
Application	CCTV Camera, IP Camera, PTZ, IR Illuminator, DVR,LED Driver, Access Control , etc.	
Size/Net Weight	22*75*30mm / 40g	
Package Dimension	26*78*32mm	
Certification	CE /RoHS	
Carton Dimension		
Carton Weight	QTY/CTN	

### Centro Technology Limited

USA Office:15322 E Valley Blvd, City of Industry, CA91746

Phone:(626)391-8868

China Office:4th Floor; Chashu 1#,Area B,HuaFeng 1st Technology,Gushu Sanwei,Xixiang,Shenzhen

Phone:0755-23200933

Website:www.centropower.com

Email:info@centropower.com