



Curtis 1236SE-5621 HPEVS AC-9 Brushless AC Motor Kit - 48 Volt



Overview

The AC-9 is an AC motor that operates at 36-60V. It can draw up to 650A producing up to 27 HP (20kW) and 70 ft-lbs (95 Nm) of torque. This kit works very well in small, lightweight applications such as small boats, dirt bikes, ATVs, golf carts, kei cars and microcars. Features include regenerative braking as well as an idle function. At 48 volts, it makes a safer low voltage system that will give you lots of reliable EV miles.

Quick Specs

- **Weight: 60 lbs**
- **Motor Case Length: 10.9"**
- **Motor Shaft Length: 2"**
- **Max Voltage Input: 60V**
- **Rated Torque: 70 ft lbs**
- **Rated Horsepower: 27 HP**
- **Max RPM: 10,000**

Kit Contents

- **HPEVS AC9 Motor**
- **Curtis 1236SE-5621 Controller**
- **35 Pin Connector and Wire Harness**
- **Gigavac GV200-QA Contactor**
- **12 Volt HV Relay**
- **Curtis 840 Dash Gauge**
- **SPST Menu Button**
- **SPST Mode Switch**

Specifications – Curtis 1238SE-6501 HPEVS AC-9 Brushless AC Motor Kit - 48 Volt

- **Motor Face:** C-Face
- **Motor Diameter:** 7.132 Inches
- **Motor Case Length:** 10.988 Inches
- **Motor Shaft Length:** 2.0 Inches
- **Motor Shaft to End Length:** 13.238 Inches
- **Motor Type:** AC Induction Brushless
- **Weight:** 50 lbs
- **Max Voltage Input:** 60V
- **Terminal Stud Size:** 5/16 Inch
- **Integrated Sensors:** Encoder and Temperature
- **Rated Torque:** 70 Lb Ft
- **Rated Power:** 27 HP
- **Max RPM:** 10,000
- **RPM Sensor:** Yes
- **Drive End Shaft:** 1-1/8 Inch with 1/4 Inch Keyway
- **Accessory End Shaft:** Optional 7/8 Inch with 3/16 keyway
- **Max Efficiency:** 88%
- **Thermal Cooling:** Internal Fan
- **Max Temperature:** 180 Degrees Celsius

