



Custom Power Cables Accessory Sizing Guide

This guide is intended to help you match your cable to the correct cable accessories.

| Cable | Lugs | | Battery Terminals | | Anderson | Sleeving | | | | |
|-----------|--------------------|------------|-------------------|------------|-----------|----------|---------|------|------|-------|
| Size | Lug Size | Insulators | Terminals | Insulators | Plug Size | Shrink | Braid | Heat | PVC | Split |
| 6mm | 6mm ² | RB8 | N/A | N/A | SB50 | 9-3mm | 3-6.4mm | 6mm | 6mm | 5mm |
| 8B&S | 10mm ² | RB8 | N/A | N/A | SB50 | 9-3mm | 3-6.4mm | 6mm | 7mm | 7mm |
| 6B&S | 16mm ² | RB3/RB6-2 | N/A | N/A | SB50 | 9-3mm | 6-11mm | 8mm | 9mm | 10mm |
| 4B&S | 25mm | RB3/RB6-2 | N/A | N/A | SB120 | 12-4mm | 6-11mm | 10mm | 12mm | 10mm |
| 3B&S | 25mm ² | RB3/RB6-2 | MA59 | Small | SB120/175 | 12-4mm | 6-11mm | 12mm | 14mm | 13mm |
| 2B&S | 35mm ² | RB6-2/RB2 | 2 | Small | SB120/175 | 12-4mm | 9-16mm | 12mm | 14mm | 13mm |
| 1B&S | 50mm ² | RB2 | 0 | Small | SB175/350 | 19-6mm | 9-16mm | 15mm | 16mm | 13mm |
| 0B&S | 50mm ² | RB2/RB00 | 0 | Large | SB175/350 | 19-6mm | 9-16mm | 15mm | 16mm | 16mm |
| 00B&S | 70mm ² | RB00 | 00 | Large | SB350 | 19-6mm | 9-16mm | 15mm | 18mm | 16mm |
| 000B&S | 95mm ² | RB000 | 000 | Large | SB350 | 19-6mm | 16-25mm | 20mm | 20mm | 20mm |
| 0000B&S | 120mm ² | RB000 | 120 | Large | N/A | 24-8mm | 16-25mm | 20mm | 20mm | 20mm |
| Twin 6mm | 6mm ² | RB8 | N/A | N/A | SB50 | 12-4mm | 6-11mm | 10mm | 12mm | 10mm |
| Twin 8B&S | 10mm ² | RB8 | N/A | N/A | SB50 | 19-6mm | 9-16mm | 12mm | 16mm | 13mm |
| Twin 6B&S | 16mm ² | RB3/RB6-2 | N/A | N/A | SB50 | 19-6mm | 9-16mm | 15mm | 18mm | 16mm |
| Twin 4B&S | 25mm ² | RB3/RB6-2 | N/A | N/A | SB120/175 | 24-8mm | 16-25mm | 20mm | 20mm | 20mm |
| Twin 2B&S | 35mm ² | RB6-2/RB2 | 2 | Small | SB120/175 | 24-8mm | 19-32mm | 25mm | 25mm | 29mm |
| Weld 35 | 35mm ² | RB2 | 2 | Small | SB120/175 | 19-6mm | 9-16mm | 15mm | 16mm | 16mm |
| Weld 50 | 50mm ² | RB00 | 0 | Large | SB175/350 | 19-6mm | 9-16mm | 20mm | 18mm | 16mm |
| Weld 70 | 70mm ² | RB000 | 00 | Large | SB350 | 24-8mm | 16-25mm | 20mm | 20mm | 20mm |
| Weld 95 | 95mm ² | RB000 | 000 | Large | SB350 | 24-8mm | 16-25mm | 25mm | 25mm | 20mm |

This is intended as a guide for the most common accessories for each cable. Please check your requirements before purchasing.