

OWNER'S INSTRUCTIONS



Rechargeable 3-in-1

LED KITS WITH INTERCHANGEABLE LIGHT HEADS

Model NT-LS002373

The NextLED innovative 3-IN-1 Quick Connect Light Kit includes a 320/140 Lumen Flashlight, a 400/160 Lumen Slim Bar Foldable Light, a 120/70 Lumen Flex-Shaft Light and a USB Charging Cord. All 3 lights are all interchangeable so you can pick the perfect light that best suits the specific working circumstances. Keep this manual for the safety warning and precautions, assembly, operating, inspection, maintenance and cleaning procedures. Keep this manual and the receipt in a safe and dry place for future reference.

CAUTION: Read all instructions and warnings before operating!
SAVE THESE INSTRUCTIONS!

WARNING: To avoid serious injury or death from electrical shock or fire:

1. This fixture **MUST ALWAYS BE USED IN ACCORDANCE WITH ALL ELECTRICAL AND SAFETY CODES AND ORDINANCES**, including the most recent National Electric Code (NEC) and with the Occupational Safety and Health Act (OSHA) Volume 1 on General Industry Standards and interpretations.
2. **ALWAYS** make certain that the power source conforms to the requirements on the fixture.
3. **DO NOT** inspect or service the fixture while charging.
4. Do not charge for longer than 4 hrs. Overcharging will cause overheating and shorten battery life.
5. **CAUTION:** Keep dry. Do not open, drop, short-circuit, incinerate, expose to temperatures higher than 140°F, or charge/use if damaged.
6. People with pacemakers should consult their physician(s) before use. Electromagnetic fields in close proximity to heart pacemaker could cause pacemaker interference or pacemaker failure
7. This fixture is not explosive-proof, **DO NOT** use in potentially dangerous locations, such as in flammable or explosive atmospheres.
8. **NEVER** operate the light with the clear protective glass broken or removed.
9. **NEVER LOOK DIRECTLY INTO LIGHT SOURCE.** LED's are extremely bright and can damage eyes with prolonged exposure.
10. **KEEP AWAY** from heating vents, radiators, or other sources of heat.
11. **KEEP OUT OF REACH OF CHILDREN.**
12. **INTENDED FOR INDOOR AND OUTDOOR USE.**

LITHIUM BATTERY SAFETY WARNINGS

LITHIUM BATTERIES STORE A LARGE AMOUNT OF ENERGY AND WILL VENT FIRE OR EXPLODE IF MISTREATED:

1. Keep work light dry.
2. **DO NOT DO ANY OF THE FOLLOWING TO BATTERY PACK:**
 - a. Drop
 - b. Open
 - c. Short-circuit
 - d. Puncture
 - e. Incinerate, or
 - f. Expose to temperatures greater than 140°F.
3. Charge work light only according to these instructions

BATTERY REPLACEMENT

1. Unthread the base of the light.
2. Remove old battery, noting polarity
3. Insert a new 18650 type 3.7V, 1800mAh li-ion battery into the light, positive end first

BATTERY CHARGING

WARNING: READ ENTIRE IMPORTANT SAFETY INFORMATION. section at the beginning of this document including all text under subheadings therein before set up or use of this product.

1. Insert the end of the charging cable into the charging jack, located on the side of the handle, under a cover.
2. Plug charging cable into a powered USB port.
3. The charging indicator button will light up red during charging. After approximately 4 hours the charging indicator turns green indicating that the work light is charged and ready for use. Unplug the charging cable.

LIGHT ATTACHMENT AND FUNCTION

1. Attach the light of your choice to the top of the base by pushing down on the light attachment to lock it in place
2. To remove the light attachment, pull down on the locking ring to release the light attachment.

OPERATING INSTRUCTIONS

WARNING: READ ENTIRE IMPORTANT SAFETY INFORMATION. section at the beginning of this document including all text under subheadings therein before set up or use of this product.

NOTE: before using work light for the first time, fully charge the battery.

Slim Bar Light:

1. Press the button once to turn on the light (160 Lumen)
2. Press the button again to switch to high mode (400 Lumen)
3. Press the button a third time to turn off the light

Flashlight:

1. Press the button once to turn on the light (140 Lumen)
2. Press the button again to switch to high mode (320 Lumen)
3. Press the button a third time to turn off the light

Flex-Shaft Light:

4. Press the button once to turn on the light (70 Lumen)
5. Press the button again to switch to high mode (120 Lumen)
6. Press the button a third time to turn off the light

ONE YEAR LIMITED WARRANTY

If this Smart Electrician® product fails due to a defect in materials or workmanship, Smart Electrician® will at its option, repair it or replace it with the same or comparable model, free of charge.

For repair or replacement under warranty, return to the retail establishment where the product was purchased.

This warranty give you specific legal rights and you may have other rights that vary from state to state.

This warranty is void if damage or defect has resulted from accident, abuse, misuse or faulty repair. In no event will Smart Electrician® be liable for any consequential, special, incidental, or indirect damages of any kind arising out of the use or misuse of this product. Maximum liability shall not in any case exceed the purchase price of the product including shipping. Some states do not allow the exclusion or limitation of incidental or consequential damages so the above exclusions or limitations may not apply to you.

SPECIFICATIONS

General:

Input Rating: 5V DC (USB charging cord can fit in with any regular 5V Charger with USB port)
Battery: Li-ion 18650 Type, 3.7V, 1800mAh
Charging Time: Approx 6 hrs (based on 1A)
Water Resistance: IPX4

Slim Bar Light:

Light Output: 400 Lumen (high), 160 Lumen (Low)
Run Time: 4 Hours (High); 8 Hours (Low)

Flashlight:

Light Output: 320 Lumen (high), 140 Lumen (Low)
Run Time: 4 Hours (High); 10 Hours (Low)

Flex-Shaft Light:

Light Output: 120 Lumen (high), 70 Lumen (Low)
Run Time: 10 Hours (High); 16 Hours (Low)

Your product, accessories and packaging should be discarded in an environmentally responsible way.

Figures and photos may vary slightly due to our program of continuous product improvements.



Your future in a better light.

© 2020 Distributed by Nextool Inc.
Schaumburg, IL
Visit mynextled.com
Customer Service: 1-877-886-6822

MADE IN CHINA