



ENGLISH

## Instruction Manual

Thank you for purchasing FANTECH CRYPTO VX7 Macro Gaming Mouse.

FANTECH CRYPTO VX7 has 10 millions switch and also support up to 8000DPI with RGB switch button, to make you pinpoint accurate and to land more killing blows when playing the game.

FANTECH CRYPTO VX7 is a plug and play usb interface programmable mouse, no need to install any driver for your first use. For more enhanced settings and function, you can install the software from our website [www.fantechworld.com](http://www.fantechworld.com)

## Technical Specification

- Gaming Optical Sensor
- On-the-fly Adjustable DPI (200-8000)
- Speed/Acceleration: 60ips/20g
- Polling Rate: 125hz
- FPS: max 6000fps
- 10,000,000 Click Lifetime
- 1.8m Nylon Braided Cable
- Silicon Rubber Roller
- RGB Chroma Luminous Light
- Size: 128mm x 68mm x 41 mm

## Size



# CRYPTO VX7

MACRO GAMING MOUSE

## What's included in the box

1. FANTECH CRYPTO VX7 Macro Gaming Mouse
1. set mouse skates
3. User manual

## System requirements

1. Operating systems: Windows XP/7/8/10; MAC OS
2. One free USB 2.0/3.0 port

USER MANUAL

## Keys Function Map



KEY	KEY FUNCTION MAP
1	LEFT BUTTON
2	MID BUTTON
3	RIGHT BUTTON
4	FORWARD
5	BACKWARD
6	DPI

## Software



### Basic setup

- \* You can program your mouse button to any multimedia function and gaming function by selecting the mouse number and select your desire command on the button assign bar.
- \* Press Apply to save changes.



### Advanced setup

- \* Customize your mouse DPI level, pointer precision, wheel speed, fire speed/ pointer speed.
- \* Press save to changes.




### LED setup

- \* Customize your LED setup to slow, fast, static and off .
- \* Press save to changes.



### Macro setting

- \* To create a new macro in settings, right click in macro list bar, input the macro folder, macro name and then input key list  
Example:
  - Add macro folder name "ASD"
  - Input the macro name "ASD"
  - Press Record Button and type "ASD" then press Stop Recording
  - You can edit delay time/cycle before saving.
  - Press save/apply button to save your macro "ASD"
- \* To use your macro "ASD"
  1. Go to button assignment bar
  2. Select button you want to apply the macro "ASD"
  3. Then select Macro and select ASD
  4. Save & Apply
 Your button will be used as "ASD"
- \* To check your Macros
  1. Go to notepad
  2. Click the assigned macro button
  3. It should type ASD
 Note: "ASD" is just an example, you can use your own keys for macros.



## How to connect

Its plug and play. Connect the mouse to computer by inserting USB jack to your computer USB port.