



# GP-BMK-25

ACCURATELY MONITOR YOUR BATTERY PERFORMANCE

## THE ULTIMATE WAY TO MONITOR YOUR BATTERY

View your battery's performance with the Go Power! Battery Monitor Kit (GP-BMK-25). Fit for all battery types, the GP-BMK-25, gives you easy to understand battery stats at the push of a button.

Monitor essential battery statistics including:

- State of Charge
- Capacity
- Voltage
- Current
- Two Battery Voltage Display

## GP-BMK-25 BATTERY MONITOR



Battery Shunt

Battery Monitor

## FEATURES

- 500-amp quick connect battery shunt connection kit
- 25-foot cable
- Low Voltage Alarm
- Low Capacity Alarm
- 3 year limited warranty



## SPECIFICATIONS

Working Voltage	10 - 120 VDC
Operating temperature range	-10 - 60°C (14 - 140°F)
Battery Bank Capacity	0.1 - 999 Ah
Working Draw	10 - 15 mA
Standby Draw	1 - 2 mAv
Accuracy	Voltage - $\pm 1.0$
	Current - $\pm 1.0$
	Capacity - $\pm 1.0$

## COMPONENTS

Battery connector (included)	500A/50mV
Cables (included)	10 meter 6 core UTP with RJ12 connectors and cable with fuse for '+' connection
INPUT WIRE for INSTALL (Sold Separately)	0.3 - 0.75mm <sup>2</sup> 28 to 20 gauge

## MOUNTING & DIMENSIONS

Installation	Flush mount
Faceplate Dimensions	3.9 x 2.4 x 0.7 in 99 x 61 x 18 mm
Weight	Faceplate: 0.1lb / 75g Package: 1.5lb / 680g



Specifications may be subject to change. Product may not be exactly as shown. Specifications subject to local environmental conditions.