

GENTECH™

Power you can trust

www.gentechgenerators.com.au



7kVA 200 Amp Welder Generator

This reliable Gentech Welder generator is powerful and built tough. With a 200 Amp Welder and 7kVA alternator this unit has everything you need for portable off grid welding. Welding leads are available as an optional Extra.

810 x 545 x 540
LxWxH

Reliable Honda
GX390 Engine

200 Amp Welder

NSM Brushless
Alternator



OPTIONAL EXTRA

10-WELD LEADS-08



	EP200WELDHSR	EP200WELDHSRE
GENERATOR	Rated Voltage	230V
	Frequency	50Hz
	Rated Output	5600 Watts
	Max. Output	7kVA
ENGINE	Engine Type	Honda GX390
	Horsepower	11HP
	Starting System	Recoil
GENERAL	Size - LxWxH (mm)	810x545x545
	Dry Weight	100kg
	Fuel Tank Capacity	6.1L
	Operating Hrs (80% Load)	2.5hr
	Fuel Consumption (80% Load)	2.44L/hr
	Noise Level (7m)	69 dbA
FEATURES	Welder Amps @ 60%	200
	Outlets	2 x 15 Amp
	Brushless Alternator	✓
	AC Welding	✓



Welder Duty Cycle: 200 Amps @ 60%

POWERED by
HONDA™

Victoria: Head Office
59 Export Drive
Brooklyn VIC 3012
Ph: +61 3 9316 9799
Fax: +61 3 9314 0909
Email: sales@wellcross.com.au

New South Wales
Unit 2/1040 Canley Vale Road
Wetherill Park NSW 2164
Ph: +61 2 9757 5800
Fax: +61 2 9757 5899
Email: nsw@wellcross.com.au

Queensland
Unit 2/55 Christensen Rd
Stapylton QLD 4207
Ph: +61 7 3386 2400
Fax: +61 7 3386 1241
Email: qld@wellcross.com.au

North Queensland
Unit 19/547 Industry Park
547-593 Woolcock St
Mount Louisa, Townsville, QLD 4814
Ph: +61 7 4774 6331
Email: nthqld@wellcross.com.au

Western Australia
Unit 8/235 Camboon Road
Malaga WA 6090
Ph: +61 8 9248 2955
Fax: +61 8 9248 2933
Email: wa@wellcross.com.au

South Australia
Ph: 0417 592 530
Email: bnicholas@wellcross.com.au