


PLUG: RA3H2-080-4EA-5900 XXXXX-XXX-XXX-XXXX



## 

6400

6500

6600

6700

Turning jackset, 490" knob

Turning jackset, reversed, 490" knob

Two turning jackscrews, 490" knob

Two turning jacksockets, 490" knob

If potting well is used with a pre-wired connector, it will be potted and not repairable. If potting well is not used with a pre-wired connector, it will not be potted. Contacts that are not potted in place can be removed and replaced only one time. See page R-33.4 for crimp instructions, contact insertion and contact removal tools.

WIRE	CODES-
------	--------

TYPE and COLOR		LENGTH		
Code Mil-W-1	<b>Size</b>	Color	Code	<b>Length</b> (+1"/-0")
A B C D E F G H J K	22 awg 22 awg 24 awg 24 awg 26 awg 26 awg 28 awg 30 awg	White Ten repeating White Ten repeating White Ten repeating	ABCDEFGHJKL	6" 12" 18" 24" 30" 36" 42" 48" 54" 60" 66"
Mil-W-22759/33			М	72"
LMNPRSTU>W	22 awg 22 awg 24 awg 24 awg 26 awg 26 awg 28 awg 28 awg 30 awg	White Ten repeating White Ten repeating White Ten repeating White White	N P R S	84" 96" 108" 120"

## USING WIRE CODES:

RA3H2-080-4EA-5900
Type and Color ———— Length

Color sequence for Ten repeating wire colors: (Beginning in position #1)

Black

Brown

Red

Orange Yellow

Yellow Green

Blue

Violet

Grey White

Repeat this sequence until connector is fully loaded.