



|              | 45           |              | 4           | Controller:  | KBS          |              |
|--------------|--------------|--------------|-------------|--------------|--------------|--------------|
| Voltage      | Amps         | Watts (in)   | Speed(rpm)  | Power (NM)   | Watts (out)  | Eff (%)      |
| 48.29        | 0.904        | 43.67        | 3493        | 0.027        | 9.738        | 22.30        |
| 48.27        | 0.997        | 48.13        | 3487        | 0.043        | 15.76        | 32.74        |
| 48.26        | 1.189        | 57.36        | 3476        | 0.071        | 25.75        | 44.89        |
| 48.25        | 1.527        | 73.70        | 3453        | 0.117        | 42.34        | 57.45        |
| 48.23        | 2.048        | 98.80        | 3418        | 0.190        | 67.97        | 68.80        |
| 48.20        | 2.807        | 135.3        | 3369        | 0.293        | 103.3        | 76.35        |
| 48.14        | 3.847        | 185.2        | 3300        | 0.439        | 151.8        | 81.97        |
| 48.13        | 5.133        | 247.0        | 3217        | 0.631        | 212.5        | 86.03        |
| 48.05        | 6.751        | 324.4        | 3113        | 0.866        | 282.4        | 87.05        |
| <b>47.99</b> | <b>8.506</b> | <b>408.2</b> | <b>2994</b> | <b>1.144</b> | <b>358.5</b> | <b>87.82</b> |
| 47.92        | 10.72        | 513.7        | 2851        | 1.480        | 442.0        | 86.04        |
| 47.85        | 12.66        | 605.6        | 2729        | 1.798        | 514.0        | 84.87        |