



	18		4	Controler:	KLS	
Voltage	Amps	Watts (in)	Speed(rpm)	Power (NM)	Watts (out)	Eff(%)
24.61	4.109	101.1	3169	0.054	17.89	17.70
24.59	4.725	116.2	3163	0.084	27.73	23.86
24.58	5.426	133.4	3156	0.151	49.89	37.40
24.54	6.722	165.0	3146	0.238	78.46	47.55
24.51	7.964	195.2	3141	0.364	119.7	61.32
24.43	10.62	259.5	3134	0.541	177.6	68.44
24.34	13.69	333.3	3081	0.774	249.8	74.95
24.22	18.06	437.5	3065	1.080	346.8	79.27
24.08	22.80	549.1	3005	1.437	452.2	82.35
23.96	27.06	648.2	2956	1.776	549.6	84.79
23.81	32.31	769.2	2904	2.163	657.6	85.49
23.67	37.82	895.3	2832	2.599	770.5	86.06
23.53	43.49	1024	2772	3.045	884.0	86.33
23.39	49.49	1158	2722	3.513	1001	86.44
23.26	55.13	1282	2652	3.975	1104	86.12
23.13	61.38	1420	2598	4.459	1213	85.42
23.00	67.71	1557	2540	4.959	1319	84.71