



	52		4	Controler:		KLS
Voltage	Amps	Watts (in)	Speed(rpm)	Power (NM)	Watts (out)	Eff(%)
72.57	1.339	97.18	3146	0.062	20.31	20.90
72.57	1.427	103.6	3147	0.079	25.87	24.97
72.55	1.723	125.0	3138	0.105	34.64	27.71
72.55	1.880	136.4	3129	0.151	49.55	36.33
72.55	1.957	141.9	3120	0.220	71.72	50.54
72.53	2.441	177.0	3129	0.307	100.7	56.89
72.51	3.058	221.7	3116	0.431	140.7	63.46
72.48	3.855	279.4	3080	0.598	192.9	69.04
72.45	4.625	335.1	3042	0.804	256.1	76.42
72.41	5.759	417.1	3098	1.035	335.7	80.48
72.36	7.106	514.2	3059	1.320	422.9	82.24
72.33	8.260	597.4	3058	1.580	506.1	84.72
72.28	9.649	697.4	3054	1.880	601.4	86.23
72.23	11.04	797.3	2993	2.236	700.8	87.90
<b>72.17</b>	<b>12.65</b>	<b>913.1</b>	<b>3003</b>	<b>2.579</b>	<b>810.9</b>	<b>88.81</b>
<b>72.12</b>	<b>14.27</b>	<b>1029</b>	<b>2957</b>	<b>2.932</b>	<b>908.0</b>	<b>88.24</b>
<b>72.06</b>	<b>15.92</b>	<b>1147</b>	<b>2945</b>	<b>3.304</b>	<b>1019</b>	<b>88.84</b>
<b>72.00</b>	<b>17.63</b>	<b>1269</b>	<b>2878</b>	<b>3.710</b>	<b>1118</b>	<b>88.10</b>
<b>71.95</b>	<b>19.25</b>	<b>1385</b>	<b>2828</b>	<b>4.120</b>	<b>1220</b>	<b>88.09</b>
71.88	21.47	1543	2837	4.562	1355	87.82
71.82	23.06	1656	2776	4.991	1451	87.62
71.76	24.86	1784	2724	5.429	1548	86.77