



	60		4	Controler:		KLS
Voltage	Amps	Watts (in)	Speed(rpm)	Power (NM)	Watts (out)	Eff(%)
48.48	0.826	40.06	1705	0.018	3.258	8.13
48.48	0.921	44.64	1706	0.037	6.583	14.75
48.47	1.073	52.03	1706	0.076	13.60	26.14
48.47	1.375	66.65	1705	0.154	27.48	41.23
48.46	1.768	85.68	1706	0.263	46.93	54.77
48.44	2.259	109.4	1706	0.401	71.54	65.39
48.42	2.836	137.4	1704	0.571	102.0	74.24
48.40	3.520	170.4	1705	0.758	135.3	79.40
48.38	4.311	208.6	1705	0.954	170.3	81.64
48.36	5.079	245.6	1705	1.164	207.9	84.65
48.33	6.030	291.5	1705	1.393	248.7	85.32
48.31	6.959	336.2	1676	1.626	285.4	84.89
48.28	7.912	382.0	1666	1.885	328.9	86.10
48.25	8.943	431.5	1651	2.157	372.9	86.42
48.22	10.05	484.6	1646	2.447	421.8	87.04
48.19	11.14	536.7	1629	2.748	468.6	87.31
48.14	12.50	602.0	1628	3.063	522.1	86.73
48.11	13.72	660.3	1623	3.401	578.0	87.54
48.07	15.07	724.5	1611	3.727	628.8	86.79
48.03	16.39	787.1	1594	4.081	680.9	86.51
47.99	17.76	852.3	1573	4.457	734.2	86.14
<b>47.94</b>	<b>19.32</b>	<b>926.0</b>	<b>1542</b>	<b>4.879</b>	<b>788.0</b>	<b>85.10</b>
47.89	20.99	1005	1528	5.323	851.7	84.75
47.84	22.45	1074	1494	5.741	898.4	83.65