



	60		6	Controller:		KLS
Voltage (v)	Current (A)	PowerIn (w)	Speed (rpm)	NM	PowerOut (w)	Eff (%)
48.72	1.072	52.20	638	0.098	6.509	12.47
48.72	1.188	57.89	633	0.233	15.42	26.64
48.72	1.527	74.38	626	0.492	32.23	43.33
48.69	2.068	100.7	635	0.868	57.69	57.29
48.67	2.806	136.6	633	1.380	91.45	66.95
48.65	3.632	176.7	628	2.008	132.1	74.76
48.63	4.505	219.1	624	2.730	178.4	81.42
48.60	5.593	271.8	621	3.528	229.4	84.40
48.58	6.133	298.0	617	3.933	254.1	85.27
48.55	7.260	352.5	619	4.772	309.3	87.74
48.53	8.288	402.2	616	5.551	358.1	89.04
48.51	9.189	445.7	612	6.256	401.2	90.02
48.48	10.13	491.1	608	6.970	443.7	90.35
48.45	11.16	540.9	607	7.699	489.7	90.53
48.42	12.20	590.9	603	8.485	535.7	90.66
48.40	13.24	641.0	600	9.297	584.1	91.12
48.37	14.36	694.5	597	10.11	632.0	91.00
48.34	15.40	744.7	595	10.94	681.7	91.54
48.33	15.94	770.6	592	11.35	703.8	91.33
48.30	17.04	822.8	591	12.16	752.9	91.50
48.27	18.03	870.5	586	12.97	796.3	91.48
48.24	19.16	924.2	585	13.75	842.9	91.20
48.21	20.21	974.5	583	14.53	887.4	91.06
48.19	21.18	1021	580	15.28	928.9	90.98
48.16	22.11	1065	577	16.01	968.1	90.90
48.14	22.98	1106	576	16.66	1006	90.96
48.11	23.75	1143	573	17.30	1039	90.90
48.09	24.40	1173	571	17.86	1068	91.05