### RUNO

# **CONNECTING 4G CAMERA TO WIFI**

Wi-Fi						
<		( <sup>33</sup> ):				
On						
Current	network					
	MIFI_6C5B Connected without internet	<ul><li>(?)</li><li>(?)</li></ul>				
Availab	le networks					
	J&E115LeeHeightsMes	sh				
	SKYQKVLV					
•8	116LeeHeights					

Go to your phones WiFi settings and find and connect to: Network name: MIFI\_XXXX Password: 1234567890

When connected, you may get a prompt advising there is no internet connection, if so ensure you stay connected to the network.







Open your phones web browser e.g. Safari, Chrome.

Type in the address bar: http://192.168.100.1

When webpage as shown above loads, enter the password: admin

### RUrelview.

# **CONNECTING 4G CAMERA TO WIFI**



# When signed in to the admin console, select the **Wi-Fi settings** option.

	192.168.1	100.1/inde	2)	+	2	:
4G		FDD	D_LTE H3G Hu	tchins II	Di ti 🔿	egout English -
<	Set up wireless hots	Wi-Fi Settir pot so that your mobile phone	<b>igs</b> e or laptop coul	d access netv	vork via it	
SSID	Wi-Fi Switch	Enable	ODisable			Apply
WPS	Internet Wi-Fi					
Internet Wi-Fi	Internet Wi-Fi Switch	Enable	ODisable			
Advanced Settings	Current Status	WAN connected				Apply
WLAN MAC Filter	0					

Copyright © 2010-2021 All rights reserved

#### Now select Internet Wi-Fi in the left hand menu.

#### Check the **Enable** radio button next to the **Internet Wi-Fi Switch** menu then click **Apply**.

This make take a few moments for the changes to apply.

	<b>1</b> 92.168.1	00.1/inde	e> +	2	:
4G			Limited Service	e 🗙 🕀 🕀	ਗ਼ থা 🗐 🛃
<	Set up wireless hotsp	Wi-Fi Setti	ngs le or laptop could acces	ss network via it	
SSID	Wi-Fi Switch	Enable	ODisable		Apply
WPS	Internet Wi-Fi				Арріу
Internet Wi-Fi	Internet Wi-Fi Switch	Enable			
Advanced Settings	Current Status	No connection			Apply
WLAN MAC Filter	Wi-Fi Hotspot				_
	Connect Delete E lit Option SSID	Add		Security Mode	
	0				
	Сору	right © 2010-2021 All rights	reserved		

# You'll now have the option to click **Add** under the **Wi-Fi Hotspot** menu.

RUrelview.

### 

## **CONNECTING 4G CAMERA TO WIFI**

	<b>A</b> 1	92.168.100	.1/inde>	+ 2 :
4G			FDD_LTE H3G H	utchins " 🕀 🏦 🏟 🔳 🛜 1
				Modify Login Password Logout English
<		Set up wireless hotspot so the	Wi-Fi Settings at your mobile phone or laptop cou	ıld access network via it
SSID	Wi-Fi Sw	iitch	Enable ODisable	
WPS	Add W	i-Fi Hotspot		Apply
Internet Wi-Fi	Network	Name(SSID) *		
Advanced Settings	Security	Mode	OPEN	<u></u>
_	Encryptic	on Type	NO ENCRYPTION	×
WLAN MAC Filter				Refresh Apply Back
		SSID	Signal	Security Mode
	0	J&E115LeeHeightsMesh	7	WPA2-PSK
	0	J&E115LeeHeightsMesh	<b>?</b>	WPA2-PSK
	0	SKYQKVLV	7	WPA2-PSK
	0	Hometelecom90HQ	7	WPA-PSK/WPA2-PSK
	0	116LeeHeights	<b>7</b>	WPA2-PSK
	0	AudioPro_C5_C554A0	<b>?</b>	OPEN
	0	SKYQVLYT	<b>1</b>	WPA2-PSK
	0	TNCAPE7D8DD	<b></b>	WPA2-PSK

Copyright © 2010-2021 All rights reserved

The camera will now search for available networks to connect to. **Find your WiFi network and select it.** If your network does not appear on this list, remove the power from your camera to restart it and try again. **We recommend connecting your camera to the WiFi where there is a strong signal, then moving it to its final installation point to test you still have a WiFi signal.** 

4G				Limited Servic	e × 🕵 🕀	•
				М	odify Login Password Log	gout Engli
<		Set up wireless hotspot so th	Wi-Fi Setti at your mobile pho	ings ne or laptop could acco	ess network via it	
SSID	Wi-Fi Sw	itch	Enable	ODisable		
WPS	Add W	i-Fi Hotspot				Apply
Internet Wi-Fi	Network Name(SSID) * Security Mode WPA Algorithms		J&E115LeeHei	ghtsMesh		
dvanced Settings			WPA2-PSK		Ý	
_				AUTO		
VLAN MAC Filter	Pass Ph	rase *	[			
			Display Passw	rord		
		SSID	Signal		Refresh Apply	Back
	۲	J&E115LeeHeightsMesh			WPA2-PSK	
	0	J&E115LeeHeightsMesh	7		WPA2-PSK	
	0	TNCAPE7D8DD	<b>R</b>		WPA2-PSK	
	0	116LeeHeights	7		WPA2-PSK	
	0	AudioPro_C5_C554A0			OPEN	
	0	116LeeHeights	<b>R</b>		WPA2-PSK	
	0	SKYQVLYT	<b>P</b>		WPA2-PSK	
		52507575252505			WIDLO DOV	

Copyright © 2010-2021 All rights reserved

When you have selected your network, the network settings will populate with your WiFi details. Select the **Auto** radio button next to the **WPA Algorithms** menu. Enter your **WiFi networks password** then click **Apply**.

	192.168.1	00.1/inde	» +	3	:
4G			Limited Service	e 🗙 🌒 🕀	gout English -
<	Set up wireless hotspo	Wi-Fi Settin	ngs e or laptop could acces	ss network via it	
SSID	Wi-Fi Switch	enable	ODisable		
WPS	Internet Wi-Fi				Apply
Internet Wi-Fi	Internet Wi-Fi Switch	Enable			
Advanced Settings	Current Status	Wi-Fi connected			Apply
WLAN MAC Filter	Wi-Fi Hotspot				
	Connect Delete Edit	Add			
	Option SSID	Signal		Security Mode	
	J&E115LeeHeights	Mesh	≜ <u>?</u>	WPA2-PSK	
	0				

Copyright © 2010-2021 All rights reserved

When successfully connected you'll be shown the the above screen.

This means you have now connected your 4G camera to your WiFi network.



To test, you will need to go back into your phones WiFi settings and **disconnect from the 'MIFI\_XXXX' network**.

Either connect back to your WiFi network or use 4G on your phone. Now open the CamhiPro app on your phone and see your camera connected - this may take a few moments to load.

If you have not already connected your camera to the app, please follow guides on https://t.ly/setupcamera