

Cisco® Compatible 1000Base-LX SMF SFP Transceiver Module - Single Mode Duplex LC 1310nm to 20Km

PART NUMBER: GLC-LH-SM20-ALG

BAR CODE: 9350784013538



Overview

This SFP (mini-GBIC) transceiver module is designed for use with Cisco network equipment and is equivalent to Cisco part number GLC-LH-SM. This transceiver is built to meet or exceed the specifications of the OEM and to comply with Multi-Source Agreement (MSA) standards. This product is 100% functionally tested, and compatibility is guaranteed. The transceiver is a hot-swappable input/output device which allows a Gigabit Ethernet port to link with a fiber optic network. OEM specific configuration data is loaded on to the EEPROM of the transceiver at the factory, allowing this transceiver to initialize and perform identically to an OEM transceiver. This transceiver may be mixed and deployed with other OEM or third party transceivers and will deliver seamless network performance.

Cisco and the Cisco logo are trademarks or registered trademarks of Cisco Systems, Inc. This product is not certified or endorsed by Cisco Systems

Peatures

- * SFP Multi-Source Agreement compliance
- *Compliant with Fiber Channel 100-SM-LC-L standard
- * Compliant with IEEE802.3z Gigabit Ethernet standard
- * Industry standard small form pluggable (SFP) package
- * Duplex LC connector
- * Differential LVPECL inputs and outputs
- * Single power supply 3.3V
- * TTL signal detect indicator
- * Hot Pluggable
- * Class 1 laser product complies with EN 60825*1
- * RoHS compliant
- * Warranty: 1 Year

Application

- * Distributed multi-processing
- * Switch to switch interface
- * High speed I/O for file server
- * Bus extension application
- * Channel extender, data storage

4 Absolute Maximum Ratings

| Parameter | Symbol | Min. | Max. | Units | Note |
|---------------------|----------------|------|------|-------|------|
| Storage Temperature | T ₁ | -40 | 85 | °C | |
| Supply Voltage | Vcc | -0.5 | 4.0 | V | |
| Input Voltage | V _n | -0.5 | Vcc | V | |
| Output Current | L. | _ | 50 | mA | |
| Operating Current | los | | 400 | mA | |

Recommended Operating Conditions

| Parameter | Symbol | Min. | Max. | Units | Note |
|---------------------|--------------------------|------|------|-------|---------------|
| Storage Temperature | T _e | 0 | 70 | °C | OP6C-S10-13-C |
| | | -40 | 85 | ℃ | OP6C-S10-13-I |
| Supply Voltage | Voc | 3.1 | 3.5 | V | |
| Supply Current | $I_{\tau x} + I_{\pi x}$ | - | 250 | mA | |



6 Transmitter Electro-optical Characteristics

Vcc = 3.1 V to 3.5 V, T_c = 0°C to 70°C (-40°C to 85°C)

| Parameter | Symbol | Min. | Тур. | Max. | Units | Note | |
|--|------------------|------|----------------|---------------------------|-------|---------|--|
| Output Optical Power 9/125 µm fiber | P _{eu} | -9.5 | - | -3 | dBm | Average | |
| Extinction Ratio | ER | 9 | - | _ | dB | | |
| Center Wavelength | λε | 1270 | 1310 | 1355 | nm | | |
| Spectral Width (RMS) | Δλ | | | 2.5 | nm | | |
| Rise/Fall Time, (20-80%) | T _e , | _ | - | 260 | рв | | |
| Relative Intensity Noise | RIN | _ | | -120 | dB/Hz | | |
| Total Jitter | TJ | _ | | 227 | рв | | |
| Output Eye | | | Compliant with | Compliant with IEEE802.3z | | | |
| Max. P., TX-DISABLE Asserted | P.,, | | | -45 | dBm | | |
| Differential Input Voltage | V.,, | 0.4 | | 2.0 | V | | |

Receiver Electro-optical Characteristics

Vcc = 3.1 V to 3.5 V, T_c = 0°C to 70°C (-40°C to 85°C)

| Parameter | Symbol | Min. | Тур. | Max. | Units | Note |
|--|-----------------|------|------|------|-------|------------------------|
| Optical Input Power-maximum | P _n | -3 | - | - | dBm | BER < 10 ⁻⁰ |
| Optical Input Power-minimum (Sensitivity) | P _{in} | | - | -20 | dBm | BER < 10 ⁴² |
| Operating Center Wavelength | λC | 1260 | | 1610 | nm | |
| Optical Return Loss | ORL | 12 | - | - | dB | |
| Signal Detect-Asserted | P. | - | | -20 | dBm | |
| Signal Detect-Deasserted | P _o | -35 | | | dBm | |
| Differential Output Voltage | V.,, | 0.5 | | 1.2 | V | |
| Data Output Rise, Fall Time (20-80%) | T _{ef} | | | 0.35 | ns | |
| Receiver Loss of Signal Output Voltage-Low | RX_LOS. | 0 | | 0.5 | V | |
| Receiver Loss of Signal Output Voltage-High | RX_LOS, | 2.4 | - | VCC | V | |